

**PROJECT MANUAL
FOR**

**MAIN CAMPUS LIGHTING REPLACEMENT FY2026
JOLIET, ILLINOIS**

OWNER

JOLIET JUNIOR COLLEGE
1215 HOUBOLT ROAD
JOLIET, ILLINOIS 60431

ARCHITECT / ENGINEER

KLUBER, INC.
41 W. BENTON STREET
AURORA, ILLINOIS 60506



JOLIET
JUNIOR COLLEGE
— 1901 —

**SECTION 00 01 01
PROJECT TITLE PAGE**

PROJECT MANUAL

FOR

MAIN CAMPUS LIGHTING REPLACEMENT FY2026

1215 HOUBOLT ROAD

JOLIET, ILLINOIS 60431

OWNER

JOLIET JUNIOR COLLEGE

1215 HOUBOLT ROAD

JOLIET, ILLINOIS 60431

ARCHITECT / ENGINEER

KLUBER ARCHITECTS + ENGINEERS

41 W. BENTON STREET

AURORA, ILLINOIS 60506

END OF DOCUMENT

**SECTION 00 01 07
SEALS PAGE**

1.01 DESIGN PROFESSIONALS' SEALS

A. ELECTRICAL
ENGINEER

B. MECHANICAL
ENGINEER

END OF DOCUMENT

SECTION 00 01 10		
TABLE OF CONTENTS		
PROCUREMENT AND CONTRACTING REQUIREMENTS		PAGES
INTRODUCTORY INFORMATION		
00 01 01	Project Title Page	00 01 01-1-1
00 01 07	Seals Page	00 01 07-1-1
00 01 10	Table of Contents	00 01 10-1-1
00 01 15	Drawing Index	00 01 15-1-1
BIDDING REQUIREMENTS		
00 43 23	Bid Fom Supplement - List of Alternates	00 43 23-1-1
SPECIFICATIONS		PAGES
DIVISION 01 -- GENERAL REQUIREMENTS		
01 23 00	Alternates	01 23 00-1-1
01 30 00	Administrative Requirements (1 page attachment)	01 30 00-1-4
01 41 00	Regulatory Requirements	01 41 00-1-2
01 42 00	References	01 42 00-1-4
01 60 00	Product Requirements (1 page attachment)	01 60 00-1-3
01 70 00	Execution and Closeout Requirements	01 70 00-1-5
01 77 00	Closeout Procedures	01 77 00-1-1
01 78 00	Closeout Submittals	01 78 00-1-3
DIVISION 02 -- EXISTING CONDITIONS		
02 84 00	Polychlorinate Biphenyl (PCB) Remediation	02 84 00-1-6
DIVISION 23 -- HEATING, VENTILATING, AND AIR-CONDITIONING (HVAC)		
23 07 13	Duct Insulation	23 07 13-1-3
23 31 00	HVAC Ducts and Casings	23 31 00-1-2
23 37 00	Air Outlets and Inlets	23 37 00-1-1
DIVISION 26 -- ELECTRICAL		
26 05 00	Basic Electrical Requirements	26 05 00-1-2
26 05 05	Selective Demolition for Electrical	26 05 05-1-2
26 05 19	Low-Voltage Electrical Power Conductors and Cables	26 05 19-1-7
26 05 26	Grounding and Bonding for Electrical Systems	26 05 26-1-3
26 05 29	Hangers and Supports for Electrical Systems	26 05 29-1-3
26 05 33.13	Conduit for Electrical Systems	26 05 33.13-1-7
26 05 33.16	Boxes for Electrical Systems	26 05 33.16-1-4
26 05 53	Identification for Electrical Systems	26 05 53-1-3
26 27 26	Wiring Devices	26 27 26-1-5
26 51 00	Interior Lighting	26 51 00-1-5

END OF SECTION

**SECTION 00 01 15
DRAWING INDEX**

GENERAL

G100 COVER SHEET, GENERAL NOTES, SYMBOLS, & DRAWING INDEX

ELECTRICAL

E410 ELECTRICAL LIGHTING PLANS - BUILDING J 1ST FLR

E420 ELECTRICAL LIGHTING PLANS - BUILDING J 2ND FLR

E430 ELECTRICAL LIGHTING PLANS - BUILDING J 3RD FLR

E440 ELECTRICAL LIGHTING PLANS - BUILDING J 4TH FLR

END OF DOCUMENT

SECTION 00 43 23
BID FORM SUPPLEMENT - LIST OF ALTERNATES

1.01 PARTICULARS

A. The following is the list of Alternates referenced in the bid submitted by:

(Bidder) _____

Dated _____ and which is an integral part of the Bid Form.

1.02 ALTERNATES LIST

A. The following amounts shall be added to or deducted from the Bid Amount. Refer to Section 01 23 00 - Alternates: Schedule of Alternates.

1. Alternate # ____: (Add) \$ _____

END OF DOCUMENT

**SECTION 01 23 00
ALTERNATES**

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Description of Alternates.
- B. Procedures for pricing Alternates.
- C. Documentation of changes to Contract Sum and Contract Time.

1.02 RELATED REQUIREMENTS

- A. Document 00 43 23 - Bid Form Supplement - List of Alternates: List of Alternates as supplement to Bid Form.

1.03 ACCEPTANCE OF ALTERNATES

- A. Alternates quoted on Bid Forms will be reviewed and accepted or rejected at Owner's option. Accepted Alternates will be identified in the Owner-Contractor Agreement.
- B. Coordinate related work and modify surrounding work to integrate the Work of each Alternate.

1.04 SCHEDULE OF ALTERNATES

- A. Alternate No. 1 - Building J Second Floor Classrooms: State the amount to be added to the Base Bid to provide additional luminaire replacement as shown on the second floor lighting plans, Sheet E420. This work includes demolition of existing luminaires, provide new luminaires, provide return grilles as required.

PART 2 PRODUCTS - NOT USED

PART 3 EXECUTION - NOT USED

END OF SECTION

SECTION 01 30 00
ADMINISTRATIVE REQUIREMENTS

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Submittals for review, information, and project closeout.
- B. Architect/Engineer-provided CAD files.
- C. Submittal procedures.

1.02 RELATED REQUIREMENTS

- A. Section 01 70 00 - Execution and Closeout Requirements: Additional coordination requirements.
- B. Section 01 78 00 - Closeout Submittals: Project record documents; operation and maintenance data; warranties and bonds.

PART 2 PRODUCTS - NOT USED

PART 3 EXECUTION

3.01 SUBMITTALS FOR REVIEW

- A. When the following are specified in individual sections, submit them for review:
 - 1. Product data.
- B. Submit to Architect/Engineer for review for the limited purpose of checking for conformance with information given and the design concept expressed in the contract documents.

3.02 ARCHITECT/ENGINEER-PROVIDED CAD FILES

- A. After the execution of the Contract, Architect/Engineer will provide, free of charge, upon receipt of a properly completed and signed request utilizing "Electronic Data Transfer Consent Form" at the end of this Specification Section, CAD files depicting graphic information for the project as follows:
 - 1. Architectural Floor Plans: Column grid, walls, floors, stairs, doors, windows, room numbers, ceiling grid, mechanical diffusers, plumbing fixtures, sprinkler heads (if depicted in Bid Documents) and lights.
- B. Contractor acknowledges and accepts that the Architectural Floor Plans do not contain structural, mechanical, electrical, plumbing, fire protection and other building systems information depicted in the Bidding Documents. Examples of information not contained in these files include, but are not limited to, title blocks, keynotes, schedules, mechanical ductwork and equipment, electrical device symbols, circuit numbers and home runs, plumbing equipment, piping runs and riser diagrams, and architectural/engineering text or details. No other CAD files, data or information will be provided.
- C. Only a request from The Contractor will be honored. Subcontractors must obtain the files from the Contractor.
- D. In submitting a request, Contractor acknowledges that:
 - 1. Architect/Engineer bears no responsibility for the data or its transmission,
 - 2. Use of the data by the Contractor or his Subcontractors in no way relieves the Contractor of his obligations under the Contract,

3. Contractor is solely liable for any and all claims arising from any and all products generated by the Contractor or its Subcontractors employing the data,
4. Contractor and its Subcontractors have a limited, non-exclusive license to use the data solely in connection with the Work of the Project.
5. Architect/Engineer retains all rights, including copyright, to the data.

3.03 NUMBER OF COPIES OF SUBMITTALS

A. Documents for Review:

1. Small Size Sheets: Not Larger Than 11 x 17 inches. Submit 2 paper copies, one of which will be retained by Architect/Engineer. Contractor shall make his own copies from the original returned by the Architect.
 - a. Contractor's Option: In lieu of paper copies indicated above, submit in Adobe PDF electronic file format via email. Architect will return a reviewed copy in Adobe PDF electronic file format via email. Create PDFs at native size and right-side up; illegible files will be rejected.
2. Large Size Sheets: Larger Than 11 x17 inches; 36 x 48 inches maximum. Submit 2 paper copies, one of which will be retained by Architect/Engineer.
 - a. Contractor's Option: In lieu of paper copies indicated above, submit in Adobe PDF electronic file format via email. Architect will return a reviewed copy in Adobe PDF electronic file format via email. Create PDFs at native size and right-side up; illegible files will be rejected.

B. Extra Copies at Project Closeout: See Section 01 78 00.

3.04 SUBMITTAL PROCEDURES

A. Product Data Procedures:

1. Submit only information required by individual specification sections.
2. Collect required information into a single submittal.
3. Do not submit (Material) Safety Data Sheets for materials or products.

B. Transmit each Submittal with a copy of approved Submittal form.

C. Transmit each Submittal with AIA Form G810.

D. Sequentially number the transmittal form. Revise Submittals with original number and a sequential alphabetic suffix.

E. Identify Project, Contractor, Subcontractor or supplier; pertinent drawing and detail number, and specification section number, as appropriate on each copy.

F. Apply Contractor's stamp, signed or initialed certifying that review, approval, verification of Products required, field dimensions, adjacent construction Work, and coordination of information is in accordance with the requirements of the Work and Contract Documents.

G. Deliver Submittals to Architect/Engineer at business address.

H. Schedule Submittals to expedite the Project, and coordinate submission of related items.

I. For each Submittal for review, allow 20 days excluding delivery time to and from the Contractor.

- J. Clearly identify variations from the Contract Documents. Regardless of the type of variation, Contractor is solely responsible for errors in the field that arise from Submittal variations from the requirements of the Contract Documents if those variations were not expressly noted to specifically identify for and describe to the reviewer the nature of the variation from the Contract Documents.
- K. Identify variations from Contract Documents and Product or system limitations that may be detrimental to successful performance of the completed Work.
- L. Correlate submitted items with specified products; clearly indicate the specified product that corresponds to each submitted item.
- M. When options or optional features available for a Product are indicated in a Submittal, and selections for those options/features are indicated in the Contract Documents, identify on the Submittal the selection indicated in the Contract Documents.
- N. Provide space for Contractor and Architect/Engineer review stamps.
- O. When revised for resubmission, using clouds, highlights or other means acceptable to the Architect, identify all changes made since previous submission. Resubmittals that do not clearly identify all changes may be delayed and/or returned to the Contractor unrevised.
- P. The Contractor is entitled to 1 Resubmittal of any Shop Drawing, Product Data, or Closeout Submittal item rejected by the Architect or returned by the Architect for further action. Thereafter, the Contractor shall pay the cost of all further Architect's reviews of Shop Drawing, Product Data or Closeout Submittal, at a rate of \$200.00/hour. Cost of such further reviews will be deducted from the Contract Sum by Change Order.
- Q. Distribute reviewed Submittals as appropriate. Instruct parties to promptly report any inability to comply with requirements.
- R. Submittals not requested will not be recognized or processed.
- S. Submittal reviews may be delayed and/or Submittals may be returned unrevised for any of the following reasons:
 - 1. Submittals submitted outside the scheduled dates of the Submittal Schedule.
 - 2. Submittals are incomplete or are missing information.
 - 3. Submittals are not submitted in accordance with procedures outlined in this Section (i.e. spec Section number not indicated, missing Contractor's review stamp, submitted items not correlated with specified products).

3.05 SUBMITTAL REVIEW

- A. Submittals for Review: Architect/Engineer will review each submittal, and approve, or take other appropriate action.
- B. Architect/Engineer's actions will be reflected by marking each returned submittal using virtual stamp on electronic submittals.
 - 1. Notations may be made directly on submitted items and/or listed on appended Submittal Review cover sheet.

END OF SECTION

ELECTRONIC DATA TRANSFER CONSENT FORM

Project Name: MAIN CAMPUS LIGHTING REPLACEMENT FY2026
1215 HOUBOLT ROAD
JOLIET, ILLINOIS 60431

Project No.: 25-292-1644

Owner: JOLIET JUNIOR COLLEGE

Your Work: _____

KLUBER, INC. (hereinafter referred to as "Kluber") an Illinois corporation, is providing electronic data to you solely at your request and for your convenience. By accepting and opening any of the electronic data files, you agree that Kluber bears no liability for the data or its transmission to you and that you are solely liable for any and all claims referring or relating to any and all products you, or your Subcontractors, may generate with the data.

You acknowledge that you have a limited non-exclusive license to use the information solely in connection with your work on the project captioned above, and that Kluber retains all rights, including copyright, to the data.

Acknowledged by: _____
(Printed Name) (Signature)

Company: _____

Date: _____ Email: _____

Architectural Floor Plans are transmitted for the contractors' use as backgrounds for shop drawings and as-built drawings, and, as such, contain graphic information for column grid, walls, floors, stairs, doors, windows, room numbers, ceiling grid, lights, diffusers and sprinkler heads where indicated on Bid Documents. Plans do not contain title blocks, keynotes, schedules, mechanical ductwork and equipment, electrical device symbols, circuit numbers and home runs, plumbing equipment, piping runs and riser diagrams, and architectural/engineering text and details. Plans depict entire floors and are not formatted, partial plans as depicted in the Bidding Documents. Files are provided in R2013 .DWG format.)

**SECTION 01 41 00
REGULATORY REQUIREMENTS**

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. General.
- B. Definitions.
- C. Quality Assurance.
- D. Regulatory Requirements.

1.02 RELATED SECTIONS

- A. Section 01 42 00 - References.

1.03 GENERAL

- A. Comply with all applicable laws, rules, regulations, codes and ordinances.
- B. If the Contractor observes that the Contract Documents may be at variance with specified codes, notify the Architect/Engineer immediately. Architect/Engineer shall issue all changes in accordance with the General Conditions.
- C. It shall not be the Contractor's primary responsibility to make certain that the Contract Documents are in accordance with all applicable laws, rules and regulations, however, when the Contractor performs work knowing or having reason to know that the work in question is contrary to applicable laws, rules, and regulations, and fails to notify the Architect/Engineer, the Contractor shall pay all costs arising therefrom.

1.04 DEFINITIONS

- A. Definitions:
 - 1. Codes: Codes are statutory requirements, rules or regulations of governmental entities.
 - 2. Standards: Standards are requirements that have been established as accepted criteria, set general consent.

1.05 QUALITY ASSURANCE

- A. The Architect/Engineer has designed the project to applicable code requirements and has copies of said codes available for the Contractor's inspection.
- B. The Contractor shall:
 - 1. Ensure that copies of codes and standards referenced herein or specified in individual specifications sections are available to Contractor's personnel, agents, and Sub-Contractors.
 - 2. Ensure that Contractor's personnel, agents, and Sub-Contractors are familiar with the workmanship and requirements of applicable codes and standards.

1.06 REGULATORY REQUIREMENTS

- A. Source and Requirements: Verify amendments with local code officials.
 - 1. Illinois Community College Board code requirements:
 - a. ICC International Building Code, 2018 Edition.

- b. ICC International Mechanical Code, 2018 Edition.
- c. National Electrical Code, 2017 Edition.
- d. NFPA No. 101 - Life Safety Code, 2018 Edition.
- 2. State code requirements:
 - a. Capital Development Board (CDB):
 - 1) Illinois Energy Conservation Code (ICC International Energy Conservation Code, 2021 Edition, with State of Illinois modifications).

PART 2 PRODUCTS - NOT USED

PART 3 EXECUTION - NOT USED

END OF SECTION

SECTION 01 42 00 REFERENCES

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Drawing symbols, abbreviations and acronyms.
- B. Definitions of terms used throughout the Contract Documents.
- C. Explanation of specification format and content.
- D. Requirements relating to referenced standards.
- E. Applicability of referenced standards.
- F. List of industry organizations and certain of their respective documents.

1.02 DRAWING SYMBOLS AND CONVENTIONS

- A. Abbreviations and graphic symbols are defined on the General Notes, Symbols & Abbreviations sheet of the drawings.
- B. Generally, symbols used on the mechanical and electrical drawings conform to those recommended by ASHRAE, though, where appropriate, these symbols are supplemented by more specific symbols as recommended by ASME, ASPE, or the IEEE.

1.03 DEFINITIONS

- A. Where the terms "indicated", "noted", "scheduled", "shown", or "specified" are used it is to help locate the reference; no limitation on location is intended except as specifically noted.
- B. Where the terms "directed", "requested", "authorized", "approved", are used as in "directed by the Architect/Engineer", no implied meaning shall be construed to extend the Architect/Engineer's responsibilities into the Contractor's purview of construction supervision.
- C. Where the term "approved" is used in conjunction with the Architect/Engineer's action on submittals, requests or applications it is limited to the duties of the Architect/Engineer as described in the Agreement, and the General and Supplemental Conditions of the Contract. Such use of the term "approval" shall not limit or release the Contractor from his responsibility to fulfill Contract requirements.
- D. Where the term "regulations" is used it means all applicable statutes, laws, ordinances, and orders issued by authorities having jurisdiction, as well as construction industry standards, rules, or conventions that address performance of the Work.
- E. Where the term "furnish" is used it means supply, deliver, and unload to the construction site ready for assembly and incorporation into the Work.
- F. Where the term "install" is used it is meant to describe operations at the job site to include unloading, assembling, placing, anchoring, finishing, protecting, cleaning and all other similar operations required to fully incorporate an item into the Work.
- G. Where the term "provide" is used it means "furnish and install" as defined above.

- H. The "Project Site" is the space available to the Contractor for performance of construction activities. The Project Site may be for the exclusive use of the Contractor and his activities or may be used in conjunction with others with others performing other construction or related activities on the Project. The Extent of the Project Site is indicated on the Drawings.

1.04 SPECIFICATION FORMAT AND CONTENT

- A. These Specifications are based on the Construction Specification Institute's 49 Division format and numbering system.
- B. Language used in the Specifications and other Contract Documents is an abbreviated type. Implied words and meanings will be appropriately interpreted.
- C. Requirements expressed in imperative and streamlined language are to be performed by the Contractor. At certain locations in the text, subjective language may be used to describe responsibilities that must be fulfilled indirectly by the Contractor or others.
1. Whenever a colon (:) is used within a sentence or phrase, it shall be construed to mean the words "shall be".
- D. Use of certain terms such as "carpentry" is not intended to imply that certain activities must be performed by accredited or unionized individuals of a corresponding generic name. The Specifications do, however, require that certain construction activities shall be performed by specialists who are recognized experts in the operations to be performed. Specialists shall be used for said activities, however the final responsibility for fulfilling the requirements of the Contract remains the Contractor's.

1.05 QUALITY ASSURANCE

- A. For products or workmanship specified by reference to a document or documents not included in the Project Manual, also referred to as reference standards, comply with requirements of the standard, except when more rigid requirements are specified or are required by applicable codes.
- B. Conform to reference standard of date of issue specified in this section, except where a specific date is established by applicable code.
- C. Obtain copies of standards when required by the Contract Documents.
- D. Maintain copy at project site during submittals, planning, and progress of the specific work, until Substantial Completion.
- E. Should specified reference standards conflict with Contract Documents, request clarification from the Architect/Engineer before proceeding.
- F. Neither the contractual relationships, duties, or responsibilities of the parties in Contract nor those of the Architect/Engineer shall be altered by the Contract Documents by mention or inference otherwise in any reference document.

1.06 APPLICABILITY OF INDUSTRY STANDARDS

- A. Construction industry standards shall have the same force and effect as if bound or copied directly in the Contract Documents, except where more stringent requirements are specified. All such applicable standards are made a part of the Contract Documents by reference.

1. Where compliance with two or more standards are referenced and conflicting requirements for quality or quantities occur, comply with the more stringent requirements. Refer questions regarding apparently conflicting standards to the Architect for a decision before proceeding.
2. The standard of quality or quantity levels specified, shown, or referenced shall be the minimum to be provided or performed. Refer questions regarding standards of minimum quality or quantity to the Architect before proceeding.

1.07 CONSTRUCTION INDUSTRY ORGANIZATIONS AND DOCUMENTS

- A. ANSI -- AMERICAN NATIONAL STANDARDS INSTITUTE
- B. ASHRAE -- AMERICAN SOCIETY OF HEATING, REFRIGERATING AND AIR-CONDITIONING ENGINEERS, INC.
- C. ASME -- THE AMERICAN SOCIETY OF MECHANICAL ENGINEERS
- D. ASTM -- AMERICAN SOCIETY FOR TESTING AND MATERIALS
- E. CPSC -- CONSUMER PRODUCTS SAFETY COMMISSION
- F. FM -- FACTORY MUTUAL RESEARCH CORPORATION
- G. ICC -- INTERNATIONAL CODE COUNCIL, INC.
- H. IEEE -- INSTITUTE OF ELECTRICAL AND ELECTRONIC ENGINEERS
- I. IESNA -- ILLUMINATING ENGINEERING SOCIETY OF NORTH AMERICA
- J. ISO -- INTERNATIONAL STANDARDS ORGANIZATION
- K. NAIMA -- NORTH AMERICAN INSULATION MANUFACTURERS ASSOCIATION
- L. NEBB -- NATIONAL ENVIRONMENTAL BALANCING BUREAU
- M. NECA -- NATIONAL ELECTRICAL CONTRACTORS ASSOCIATION
- N. NEMA -- NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION
- O. NETA -- INTERNATIONAL ELECTRICAL TESTING ASSOCIATION
- P. NFPA -- NATIONAL FIRE PROTECTION ASSOCIATION
- Q. SMACNA -- SHEET METAL AND AIR CONDITIONING CONTRACTORS' NATIONAL ASSOCIATION, INC.
- R. UL -- UNDERWRITERS LABORATORIES INC.

1.08 UNITED STATES GOVERNMENT AND RELATED AGENCIES/DOCUMENTS

- A. CFR -- CODE OF FEDERAL REGULATIONS
- B. CPSC -- CONSUMER PRODUCTS SAFETY COMMISSION
- C. EPA -- ENVIRONMENTAL PROTECTION AGENCY
- D. FS -- FEDERAL SPECIFICATIONS AND STANDARDS (General Services Administration)
- E. GSA -- U.S. GENERAL SERVICES ADMINISTRATION

1.09 STATE GOVERNMENT AND RELATED AGENCIES/DOCUMENTS

- A. CDB -- ILLINOIS CAPITAL DEVELOPMENT BOARD
- B. IDOL -- ILLINOIS DEPARTMENT OF LABOR
- C. IDPH -- ILLINOIS DEPARTMENT OF PUBLIC HEALTH
- D. IEPA -- ILLINOIS ENVIRONMENTAL PROTECTION AGENCY
- E. OSFM -- OFFICE OF THE ILLINOIS STATE FIRE MARSHAL.

PART 2 PRODUCTS - NOT USED

PART 3 EXECUTION - NOT USED

END OF SECTION

**SECTION 01 60 00
PRODUCT REQUIREMENTS**

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. General product requirements.
- B. Transportation, handling, storage and protection.
- C. Product option requirements.

1.02 SUBMITTALS

- A. Product Data Submittals: Submit manufacturer's standard published data. Mark each copy to identify applicable products, models, options, and other data. Supplement manufacturers' standard data to provide information specific to this Project.

PART 2 PRODUCTS

2.01 NEW PRODUCTS

- A. Provide new products unless specifically required or permitted by the Contract Documents.
- B. Designed, manufactured, and tested in accordance with industry standards.

2.02 PRODUCT OPTIONS

- A. Products Specified by Reference Standards or by Description Only: Use any product meeting those standards or description.
- B. Products Specified by Naming One or More Manufacturers: Use a product of one of the manufacturers named and meeting specifications, no options or substitutions allowed.
- C. Products Specified by Naming One or More Manufacturers with a Provision for Substitutions: Submit a request for substitution for any manufacturer not named.

PART 3 EXECUTION

3.01 TRANSPORTATION AND HANDLING

- A. Package products for shipment in manner to prevent damage; for equipment, package to avoid loss of factory calibration.
- B. If special precautions are required, attach instructions prominently and legibly on outside of packaging.
- C. Coordinate schedule of product delivery to designated prepared areas in order to minimize site storage time and potential damage to stored materials.
- D. Transport and handle products in accordance with manufacturer's instructions.
- E. Transport materials in covered trucks to prevent contamination of product and littering of surrounding areas.
- F. Promptly inspect shipments to ensure that products comply with requirements, quantities are correct, and products are undamaged.

- G. Provide equipment and personnel to handle products by methods to prevent soiling, disfigurement, or damage, and to minimize handling.
- H. Arrange for the return of packing materials, such as wood pallets, where economically feasible.

3.02 STORAGE AND PROTECTION

- A. Designate receiving/storage areas for incoming products so that they are delivered according to installation schedule and placed convenient to work area in order to minimize waste due to excessive materials handling and misapplication.
- B. Store and protect products in accordance with manufacturers' instructions.
- C. Store with seals and labels intact and legible.
- D. Store sensitive products in weather tight, climate controlled, enclosures in an environment favorable to product.
- E. Protect products from damage or deterioration due to construction operations, weather, precipitation, humidity, temperature, sunlight and ultraviolet light, dirt, dust, and other contaminants.
- F. Comply with manufacturer's warranty conditions, if any.
- G. Cover products subject to deterioration with impervious sheet covering. Provide ventilation to prevent condensation and degradation of products.
- H. Prevent contact with material that may cause corrosion, discoloration, or staining.
- I. Provide equipment and personnel to store products by methods to prevent soiling, disfigurement, or damage.
- J. Arrange storage of products to permit access for inspection. Periodically inspect to verify products are undamaged and are maintained in acceptable condition.

END OF SECTION

SUBSTITUTION REQUEST FORM

PROJECT: 1644 – JJC – MAIN CAMPUS LIGHTING REPLACEMENT FY2026

SPECIFIED ITEM: _____

Specification Section	Page	Paragraph	Description
-----------------------	------	-----------	-------------

The undersigned requests consideration of the following:

PROPOSED SUBSTITUTION: _____

Attached data includes project description, specifications, drawings, photographs, performance and test data adequate for evaluation of the request; applicable portions of the data are clearly identified.

Attached data also includes a description of changes to the Contract Documents which the proposed substitution will require for its proper installation.

The undersigned certifies that the following paragraphs, unless modified by attachments, are correct:

1. The proposed substitution does not affect dimensions shown on drawings.
2. The undersigned will pay for changes to the building design, including engineering design, detailing, and construction costs caused by the requested substitution.
3. The proposed substitution will have no adverse effect on other trades, the construction schedule, or specified warranty requirements.
4. Maintenance and service parts will be locally available for the proposed substitution.

The undersigned further states that the function, appearance, and quality of the proposed substitution are equivalent or superior to the specified item.

Printed Name_____
Signature_____
Date_____
Firm_____
Telephone_____
Email

Attachments (list): _____

For Use By The Architect/Engineer:

☐ Accepted ☐ Accepted As Noted☐ Not Accepted ☐ Received Too Late

By: _____

Date: _____

Remarks: _____

SECTION 01 70 00
EXECUTION AND CLOSEOUT REQUIREMENTS

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Examination, preparation, and general installation procedures.
- B. Cutting and patching.
- C. Cleaning and protection.
- D. Closeout procedures, including Contractor's Correction Punch List, except payment procedures.

1.02 RELATED REQUIREMENTS

- A. Section 01 78 00 - Closeout Submittals: Project record documents, operation and maintenance data, warranties.

1.03 SUBMITTALS

- A. See Section 01 30 00 - Administrative Requirements, for submittal procedures.
- B. Cutting and Patching: Submit written request in advance of cutting or alteration that affects:
 - 1. Structural integrity of any element of Project.
 - 2. Integrity of weather exposed or moisture resistant element.
 - 3. Efficiency, maintenance, or safety of any operational element.
 - 4. Visual qualities of sight exposed elements.
 - 5. Work of Owner or separate Contractor.

1.04 PROJECT CONDITIONS

- A. Ventilate enclosed areas to assist cure of materials, to dissipate humidity, and to prevent accumulation of dust, fumes, vapors, or gases.
- B. Dust Control: Execute work by methods to minimize raising dust from construction operations. Provide positive means to prevent air-borne dust from dispersing into atmosphere and over adjacent property.
 - 1. Provide dust-proof barriers between construction areas and areas continuing to be occupied by Owner.
- C. Noise Control: Provide methods, means, and facilities to minimize noise produced by construction operations.
- D. Pest and Rodent Control: Provide methods, means, and facilities to prevent pests and insects from damaging the work.
- E. Rodent Control: Provide methods, means, and facilities to prevent rodents from accessing or invading premises.
- F. Pollution Control: Provide methods, means, and facilities to prevent contamination of soil, water, and atmosphere from discharge of noxious, toxic substances, and pollutants produced by construction operations. Comply with federal, state, and local regulations.

1.05 COORDINATION

- A. Coordinate scheduling, submittals, and work of the various sections of the Project Manual to ensure efficient and orderly sequence of installation of interdependent construction elements, with provisions for accommodating items installed later.
- B. Coordinate space requirements, supports, and installation of mechanical and electrical work that are indicated diagrammatically on Drawings. Follow routing shown for pipes, ducts, and conduit, as closely as practicable; place runs parallel with lines of building. Utilize spaces efficiently to maximize accessibility for other installations, for maintenance, and for repairs.
- C. Coordinate completion and clean-up of work of separate sections.

PART 2 PRODUCTS - NOT USED

2.01 PATCHING MATERIALS

- A. New Materials: As specified in product sections; match existing products and work for patching and extending work.
- B. Type and Quality of Existing Products: Determine by inspecting and testing products where necessary, referring to existing work as a standard.

PART 3 EXECUTION

3.01 EXAMINATION

- A. Verify that existing site conditions and substrate surfaces are acceptable for subsequent work. Start of work means acceptance of existing conditions.
- B. Verify that existing substrate is capable of structural support or attachment of new work being applied or attached.
- C. Examine and verify specific conditions described in individual specification sections.
- D. Take field measurements before confirming product orders or beginning fabrication, to minimize waste due to over-ordering or misfabrication.
- E. Prior to Cutting: Examine existing conditions prior to commencing work, including elements subject to damage or movement during cutting and patching. After uncovering existing work, assess conditions affecting performance of work. Beginning of cutting or patching means acceptance of existing conditions.

3.02 PREPARATION

- A. Clean substrate surfaces prior to applying next material or substance.
- B. Seal cracks or openings of substrate prior to applying next material or substance.
- C. Apply manufacturer required or recommended substrate primer, sealer, or conditioner prior to applying any new material or substance in contact or bond.

3.03 GENERAL INSTALLATION REQUIREMENTS

- A. Install products as specified in individual sections, in accordance with manufacturer's instructions and recommendations, and so as to avoid waste due to necessity for replacement.

- B. Make consistent texture on surfaces, with seamless transitions, unless otherwise indicated.
- C. Make neat transitions between different surfaces, maintaining texture and appearance.

3.04 ALTERATIONS

- A. Drawings showing existing construction and utilities are based on casual field observation and existing record documents only.
 - 1. Verify that construction and utility arrangements are as indicated.
 - 2. Report discrepancies to Architect/Engineer before disturbing existing installation.
 - 3. Beginning of alterations work constitutes acceptance of existing conditions.
- B. Keep areas in which alterations are being conducted separated from other areas that are still occupied.
- C. Remove existing work as indicated and as required to accomplish new work.
 - 1. Remove items indicated on Drawings.
 - 2. Relocate items indicated on Drawings.
 - 3. Where new surface finishes are to be applied to existing work, perform removals, patch, and prepare existing surfaces as required to receive new finish; remove existing finish if necessary for successful application of new finish.
 - 4. Where new surface finishes are not specified or indicated, patch holes and damaged surfaces to match adjacent finished surfaces as closely as possible.
- D. Protect existing work to remain.
 - 1. Prevent movement of structure; provide shoring and bracing if necessary.
 - 2. Perform cutting to accomplish removals neatly and as specified for cutting new work.
 - 3. Repair adjacent construction and finishes damaged during removal work.
- E. Adapt existing work to fit new work: Make as neat and smooth transition as possible.
- F. Patching: Where the existing surface is not indicated to be refinished, patch to match the surface finish that existed prior to cutting. Where the surface is indicated to be refinished, patch so that the substrate is ready for the new finish.
- G. Refinish existing surfaces as indicated:
 - 1. Where rooms or spaces are indicated to be refinished, refinish all visible existing surfaces to remain to the specified condition for each material, with a neat transition to adjacent finishes.
 - 2. If mechanical or electrical work is exposed accidentally during the work, re-cover and refinish to match.
- H. Clean existing systems and equipment.
- I. Remove demolition debris and abandoned items from alterations areas and dispose of off-site; do not burn or bury.
- J. Do not begin new construction in alterations areas before demolition is complete.
- K. Comply with all other applicable requirements of this section.

3.05 CUTTING AND PATCHING

- A. Whenever possible, execute the work by methods that avoid cutting or patching.

- B. See Alterations article above for additional requirements.
- C. Perform whatever cutting and patching is necessary to:
 - 1. Complete the work.
 - 2. Fit products together to integrate with other work.
 - 3. Provide openings for penetration of mechanical, electrical, and other services.
 - 4. Match work that has been cut to adjacent work.
 - 5. Repair areas adjacent to cuts to required condition.
 - 6. Repair new work damaged by subsequent work.
 - 7. Remove samples of installed work for testing when requested.
 - 8. Remove and replace defective and non-conforming work.
- D. Execute work by methods that avoid damage to other work and that will provide appropriate surfaces to receive patching and finishing. In existing work, minimize damage and restore to original condition.
- E. Employ original installer to perform cutting for weather exposed and moisture resistant elements, and sight exposed surfaces.
- F. Cut rigid materials using masonry saw or core drill. Pneumatic tools not allowed without prior approval.
- G. Restore work with new products in accordance with requirements of Contract Documents.
- H. Fit work air tight to pipes, sleeves, ducts, conduit, and other penetrations through surfaces.
- I. At penetrations of fire rated walls, partitions, ceiling, or floor construction, completely seal voids with fire rated material , to full thickness of the penetrated element.
- J. Patching:
 - 1. Finish patched surfaces to match finish that existed prior to patching. On continuous surfaces, refinish to nearest intersection or natural break. For an assembly, refinish entire unit.
 - 2. Match color, texture, and appearance.
 - 3. Repair patched surfaces that are damaged, lifted, discolored, or showing other imperfections due to patching work. If defects are due to condition of substrate, repair substrate prior to repairing finish.

3.06 PROTECTION OF INSTALLED WORK

- A. Protect installed work from damage by construction operations.
- B. Provide special protection where specified in individual specification sections.
- C. Provide temporary and removable protection for installed products. Control activity in immediate work area to prevent damage.
- D. Provide protective coverings at walls, projections, jambs, sills, and soffits of openings.
- E. Protect finished floors, stairs, and other surfaces from traffic, dirt, wear, damage, or movement of heavy objects, by protecting with durable sheet materials.
- F. Prohibit traffic or storage upon waterproofed or roofed surfaces. If traffic or activity is necessary, obtain recommendations for protection from waterproofing or roofing material manufacturer.

G. Remove protective coverings when no longer needed; reuse or recycle coverings if possible.

3.07 ADJUSTING

A. Adjust operating products and equipment to ensure smooth and unhindered operation.

3.08 FINAL CLEANING

A. Execute final cleaning prior to final project assessment.

1. Clean areas to be occupied by Owner prior to final completion before Owner occupancy.

B. Use cleaning materials that are nonhazardous.

C. Remove waste, surplus materials, trash/rubbish, and construction facilities from the site; dispose of in legal manner; do not burn or bury.

3.09 CLOSEOUT PROCEDURES

A. See Section 01 77 00 for additional requirements.

B. Accompany Project Coordinator on preliminary inspection to determine items to be listed for completion or correction in the Contractor's Correction Punch List for Contractor's Notice of Substantial Completion.

C. Notify Architect/Engineer when work is considered ready for Architect/Engineer's Substantial Completion inspection.

D. Submit written certification containing Contractor's Correction Punch List, that Contract Documents have been reviewed, work has been inspected, and that work is complete in accordance with Contract Documents and ready for Architect/Engineer's Substantial Completion inspection.

E. Conduct Substantial Completion inspection and create Final Correction Punch List containing Architect/Engineer's and Contractor's comprehensive list of items identified to be completed or corrected and submit to Architect/Engineer.

F. Correct items of work listed in Final Correction Punch List and comply with requirements for access to Owner-occupied areas.

G. Notify Architect/Engineer when work is considered finally complete and ready for Architect/Engineer's Substantial Completion final inspection.

H. Complete items of work determined by Architect/Engineer listed in executed Certificate of Substantial Completion.

END OF SECTION

**SECTION 01 77 00
CLOSEOUT PROCEDURES**

PART 1 GENERAL

1.01 SECTION INCLUDES:

- A. Substantial Completion Procedures.
- B. Final Completion Procedures.

1.02 RELATED REQUIREMENTS:

- A. Section 01 78 00 - Closeout Submittals.

1.03 SUBSTANTIAL COMPLETION PROCEDURES

- A. Substantial Completion Procedures:
 - 1. When the Work or a portion of the Work is considered to be substantially complete, the Contractor inspects the project and prepares a comprehensive list of outstanding items to be completed or corrected, Initial Punch List.
 - 2. Contractor submits notice of Substantial Completion.
 - 3. Contractor completes items on the Initial Punch List.
 - 4. Architect/Engineer inspects the project to verify substantial completion and prepares a Final Punch List.
 - 5. Architect/Engineer prepares Certificate of Substantial Completion, acceptance is required by Owner and Contractor.

1.04 FINAL COMPLETION PROCEDURES

- A. Final Completion Procedures:
 - 1. When items on Initial and Final Punch Lists are complete, the Contractor submits notice of final completion and final application for payment.
 - 2. Contractor submits Final Closeout Submittals as specified in Section 01 78 00.
 - 3. Architect inspects project and verifies the Work is acceptable and conforms with the Contract Documents.
 - 4. Architect processes final application for payment and closeout submittals.

1.05 CORRECTION PERIOD

- A. Correction Period commences on the date of Substantial Completion and expires one year from that date.
- B. Owner: document non-conforming or defective work over course of Correction Period. Notify Contractor in writing of nonconforming or defective work. Copy Architect/Engineer.
 - 1. Life safety issues requiring immediate corrective work: Contact Contractor for action.

PART 2 PRODUCTS - NOT USED.

PART 3 EXECUTION - NOT USED.

END OF SECTION

**SECTION 01 78 00
CLOSEOUT SUBMITTALS**

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Project Record Documents.
- B. Warranties and bonds.

1.02 RELATED REQUIREMENTS

- A. Section 01 30 00 - Administrative Requirements: Submittals procedures, shop drawings, product data, and samples.
- B. Section 01 70 00 - Execution and Closeout Requirements: Contract closeout procedures.
- C. Individual Product Sections: Warranties required for specific products or Work.

1.03 SUBMITTALS

- A. Project Record Documents: Submit documents to Architect/Engineer with claim for final Application for Payment.
- B. Warranties and Bonds:
 - 1. For equipment or component parts of equipment put into service during construction with Owner's permission, submit documents within 10 days after acceptance.
 - 2. Make other submittals within 10 days after Date of Substantial Completion, prior to final Application for Payment.
 - 3. For items of Work for which acceptance is delayed beyond Date of Substantial Completion, submit within 10 days after acceptance, listing the date of acceptance as the beginning of the warranty period.

PART 2 PRODUCTS - NOT USED

PART 3 EXECUTION

3.01 PROJECT RECORD DOCUMENTS

- A. Maintain on site one set of the following record documents; record actual revisions to the Work:
 - 1. Drawings.
 - 2. Specifications.
 - 3. Addenda.
 - 4. Change Orders and other modifications to the Contract.
 - 5. Reviewed shop drawings, product data, and samples.
 - 6. Manufacturer's instruction for assembly, installation, and adjusting.
- B. Ensure entries are complete and accurate, enabling future reference by Owner.
- C. Store record documents separate from documents used for construction.
- D. Record information concurrent with construction progress.
- E. Specifications: Legibly mark and record at each product section description of actual products installed, including the following:

1. Manufacturer's name and product model and number.
2. Product substitutions or alternates utilized.
3. Changes made by Addenda and modifications.

F. Record Drawings : Legibly mark each item to record actual construction including:

3.02 OPERATION AND MAINTENANCE DATA FOR MATERIALS AND FINISHES

- A. For Each Product, Applied Material, and Finish:
 1. Product data, with catalog number, size, composition, and color and texture designations.
 2. Information for re-ordering custom manufactured products.
- B. Instructions for Care and Maintenance: Manufacturer's recommendations for cleaning agents and methods, precautions against detrimental cleaning agents and methods, and recommended schedule for cleaning and maintenance.
- C. Additional information as specified in individual product specification sections.
- D. Where additional instructions are required, beyond the manufacturer's standard printed instructions, have instructions prepared by personnel experienced in the operation and maintenance of the specific products.

3.03 ASSEMBLY OF OPERATION AND MAINTENANCE MANUALS

- A. Assemble operation and maintenance data into PDF file "manual" for Owner's personnel use, with data arranged in the same sequence as, and bookmarked by, the specification sections.
 1. Media: USB flash drive of capacity sufficient to store entire PDF file, fragmented.
 2. Attach a tag or label flash drive with Project name, date, and the title "O&M Manual".
- B. Where systems involve more than one specification section, provide separate bookmark for each system.
- C. Prepare instructions and data by personnel experienced in maintenance and operation of described products.
- D. Prepare data in the form of an instructional manual.
- E. Cover Page: Populate the first page of the PDF file with: printed title "OPERATION AND MAINTENANCE MANUAL; identify title of Project; identify subject matter of contents.
- F. Project Directory: Beginning on the second page of the PDF file; provide Title and address of Project; names, addresses, and telephone numbers of Architect/Engineer, Consultants, Contractor and subcontractors, with names of responsible parties.
- G. Table of Contents: List every item identified by a bookmark, using the same identification as in the title of the bookmark.
- H. Bookmarks: Bookmark each separate product and system; identify the contents in the title of the bookmark; on the bookmarked page provide a description of product and major component parts of equipment.
- I. Content: Manufacturer's printed data, legibly scanned, in color where applicable, at 300 dpi resolution.

- J. Drawings: Legibly scanned, in color where applicable, at 300 dpi resolution; PDF file page size to match native sheet size of original drawing.
- K. Arrangement of Contents: Organize each volume in parts as follows:
 - 1. Project Directory.
 - 2. Table of Contents, of all volumes, and of this volume.
 - 3. Operation and Maintenance Data: Arranged by system, then by product category.
 - a. Source data.
 - b. Product data, shop drawings, and other submittals.
 - c. Operation and maintenance data.
 - d. Field quality control data.
 - e. Warranties and bonds.

3.04 WARRANTIES AND BONDS

- A. Obtain warranties and bonds, executed in duplicate by responsible Subcontractors, suppliers, and manufacturers, within 10 days after completion of the applicable item of work. Except for items put into use with Owner's permission, leave date of beginning of time of warranty until Date of Substantial completion is determined.
- B. Verify that documents are in proper form, contain full information, and are notarized.
- C. Co-execute submittals when required.
- D. Retain warranties and bonds until time specified for submittal.
- E. Include color, 300 dpi resolution scans of each in Operation and Maintenance Manual PDF file, bookmarked indexed separately in Table of Contents.
- F. Manual: Bind original copies of warranties and bonds in commercial quality 8-1/2 by 11 inch three D side ring binders with durable plastic covers.
- G. Cover: Identify each binder with typed or printed title WARRANTIES AND BONDS, with title of Project; name, address and telephone number of Contractor and equipment supplier; and name of responsible company principal.
- H. Table of Contents: Neatly typed, in the sequence of the Table of Contents of the Project Manual, with each item identified with the number and title of the specification section in which specified, and the name of product or work item.
- I. Separate each warranty or bond with index tab sheets keyed to the Table of Contents listing. Provide full information, using separate typed sheets as necessary. List Subcontractor, supplier, and manufacturer, with name, address, and telephone number of responsible principal.

END OF SECTION

SECTION 02 84 00
POLYCHLORINATE BIPHENYL (PCB) REMEDIATION

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Furnish labor, materials, services, and equipment necessary for complete removal and disposal of the following demolition debris in accordance with federal, state, and local regulations:
 - 1. PCB- and DEHP-containing lighting ballasts.
 - 2. Mercury-containing lamps and tubes, including fluorescent lamps, high intensity discharge (HID), arc lamps, ultra-violet, high pressure sodium, mercury vapor, ignitron tubes, neon, and incandescent.
- B. Perform PCB removal and disposal work in accordance with 40 CFR 761 and the requirements specified herein.

1.02 DEFINITIONS

- A. Toxic Substances: PCBs, mercury, and other substances regulated under the U.S. Federal Toxic Substances Control Act (TSCA); substances covered by this specification are identified under SECTION INCLUDES.
- B. Leak: Leak or leaking means any instance of a toxic substance present on any portion of the external surface of an item of equipment or container.
- C. PCBs: PCBs as used in this specification shall mean the same as PCBs, PCB Article, PCB Article Container, PCB Container, PCB Equipment, PCB Item, PCB Transformer, PCB-Contaminated Electrical Equipment, as defined in 40 CFR 761, Section 3, Definitions.
- D. Spill: Spill means both intentional and unintentional spills, leaks, and other uncontrolled discharges when the release results in any quantity of toxic substances running off or about to run off the external surface of an item of equipment or other source, as well as the contamination resulting from those releases.

1.03 REFERENCE STANDARDS

- A. 29 CFR 1910.132-138 - Personal Protective Equipment; Current Edition.
- B. 29 CFR 1910.145 - Accident Prevention Signs and Tags; Current Edition.
- C. 40 CFR 273 - Standards For Universal Waste Management; current edition.
- D. 40 CFR 761 - Polychlorinated Biphenyls (PCBs) Manufacturing, Processing, Distribution In Commerce, And Use Prohibitions; current edition.
- E. 49 CFR 178 - Specifications for Packaging; current edition.

PART 2 PRODUCTS

2.01 EQUIPMENT

- A. Special Clothing (PPE): Work clothes shall consist of personal protective equipment (PPE) as required by 29 CFR 1910.132-138; including, but not limited to, the following:
 - 1. Disposable coveralls.

2. Gloves (Disposable rubber gloves may be worn under these).
 3. Disposable foot covers (polyethylene).
 4. Chemical safety goggles.
 5. Half mask cartridge respirator.
- B. Special Clothing for Owner's Personnel Required to Enter Control Areas: Provide PPE same as specified for workers.
- C. PCB Spill Kit: Include the following items, in at least the quantity indicated:
1. Disposable Gloves (Polyethylene): 6 Pairs.
 2. Gloves With A High Degree Of Impermeability To PCB: 6 Pairs
 3. Disposable Coveralls With Permeation Resistance To PCB: 4 Each.
 4. Chemical Safety Goggles: 2 Each.
 5. Disposable Foot Covers (Polyethylene): 6 Pairs.
 6. PCB Caution Sign: "PCB Spill--Authorized Personnel Only": 2 Each.
 7. Banner Guard Or Equivalent Banner Material: 100 feet.
 8. Absorbent Material.
 9. Blue Polyethylene Waste Bags: 5 Bags.
 10. Cloth Backed Tape: 5 Each.
 11. Area Access Logs, Blank: 1 Roll.
 12. Brattice Cloth 6 by 6 feet: 10 Each.
 13. Rags: 1 Piece.
 14. Ball Point Pens: 20 Each.
 15. Herculite, 4 by 4 feet: 2 Each.
 16. Herculite, 8 by 8 feet: 1 Each.
 17. Blank Metal Signs And Grease Pencils.
 18. Waste Containers: 55 gallon: 2 Each.
 19. Drum (May Be Used As Container For Kit): 1 Each.
- D. PCB Caution Labels: Comply with 40 CFR 761, Subpart C.
1. Affix labels to PCB waste containers and PCB-contaminated items not stored in containers.
 2. Provide label with sufficient print size to be clearly legible, with bold print on contrasting background, displaying the following: "CAUTION: Contains PCBs (Polychlorinated Biphenyls)."
- E. Caution Signs: Comply with 29 CFR 1910.145.
1. Provide signs at approaches to Control Areas.
 2. Locate signs at such a distance that personnel may read the sign and take the necessary precautions before entering the control area.
- F. Storage Containers for PCBs: Comply with 49 CFR 178.
1. Liquid PCBs: Department of Transportation (DOT) Specification 17E containers.
 2. Non-Liquid PCB Mixtures, Articles, and Equipment: DOT Specification 5, 5B, or 17C containers with removable heads.
- G. Storage Containers for Mercury-Containing Lamps: Appropriate DOT containers (original transport boxes or equivalent).

PART 3 EXECUTION

3.01 PREPARATION

- A. Control Area: Isolate Control Area by physical boundaries to prevent unauthorized entry of personnel; do not permit food, drink, or smoking materials in areas where toxic substances are handled or stored.

3.02 WORK PROCEDURE - PCBs

- A. Permissible Exposure Limits (PEL): PEL for PCBs is 3.1 E-08 pounds per cubic foot on an 8-hour time weighted average basis.
- B. Work Operations: Ensure that work operations and processes involving PCB or PCB-contaminated materials are conducted in accordance with 40 CFR 761 and the applicable requirements of this section, including but not limited to:
 - 1. Obtaining advance approval of PCB storage sites.
 - 2. Notifying Owner prior to commencing the operation.
 - 3. Reporting leaks and spills to Owner.
 - 4. Cleaning up spills.
 - 5. Maintaining access log of employees working in Control Area and providing copy to Owner upon completion of the operation.
 - 6. Inspecting PCB and PCB-contaminated items and waste containers for leaks and forwarding copies of inspection reports to Owner.
 - 7. Maintaining the specified spill kit.
 - 8. Maintaining inspection, inventory and spill records.
- C. Perform PCB removal as described in PCB Removal Work Plan; handle PCBs so that no skin contact occurs.
- D. Personnel Protection: Require workers to wear and use PPE, as recommended by the Industrial Hygienist, upon entering PCB control area. If PPE is not required by the CIH, so state in PCB Removal Work Plan.
- E. Footwear: Keep work footwear inside work area until completion of removal operations.
- F. Hazards:
 - 1. Do not expose PCBs to open flames or other high temperature sources since toxic decomposition by-products may be produced.
 - 2. Do not heat or handle PCBs to temperatures of 135 degrees F or higher without Owner's concurrence.
- G. Package, mark, transport, and dispose of PCBs as required by regulations.
- H. Control Area: Allow only personnel certified as having received specified training into the control area.
- I. No Smoking: Smoking is not permitted within 50 feet of control area; provide "No Smoking" signs as directed by Owner.
- J. Confined Spaces: Wherever feasible, do not carry out PCB handling operations in confined spaces having limited means of egress and inadequate cross ventilation.

- K. Exhaust Ventilation: If used, discharge exhaust ventilation for PCB operations to outside and away from personnel.
- L. Solvent Cleaning: Clean contaminated tools, containers, etc., after use by rinsing three times with appropriate solvent or by wiping down three times with solvent wetted rag; suggested solvents are Stoddard solvent and hexane.
- M. Drip Pans: Place drip pans under portable PCB transformers and rectifiers in use or stored for use; provide pans with containment volume of at least one and one-half times internal volume of PCBs that would drain into pan.
- N. Evacuation Procedures: Establish written procedures for evacuation of injured workers; do not delay aid for a seriously injured worker for reasons of decontamination.

3.03 BALLASTS

- A. As ballasts are removed from lighting fixtures, inspect label on ballast.
 - 1. Ballasts Without "No PCB" Label: Assume to contain PCBs; containerize and dispose of as specified.
 - 2. Ballasts With "No PCB" Label: If there are less than 1600 total to be removed from project, dispose of them as normal demolition debris.
- B. More Than 1600 "No PCB" Labeled Ballasts: Determine whether the "No PCB" labeled ballasts contain diethylhexyl phthalate (DEHP) either by testing or by checking with ballast manufacturer indicated on the label.
 - 1. Submit testing results and/or written confirmation from manufacturer to Owner.
 - 2. If the ballasts do not contain DEHP, dispose of them as normal demolition debris.
 - 3. If they do contain DEHP, dispose of them as as specified for PCBs.
 - 4. As basis of contract assume ballasts with "No PCB" labels do not contain DEHP.
 - 5. If 1600 or more DEHP ballasts are disposed of in a 24 hour period, notify the National Response Team at 800-424-8802.

3.04 MERCURY-CONTAINING LIGHTING LAMPS

- A. Lighting Lamps: Remove lighting tubes/lamps from lighting fixtures and carefully place, unbroken, into containers.
 - 1. In the event a lighting tube/lamp breaks, sweep up pieces and contents and place waste in double plastic taped bags and dispose of as Universal Waste as specified in 40 CFR 273.
- B. Deliver unbroken, boxed, lamps to Owner at location directed.

3.05 PCB SPILL CLEANUP REQUIREMENTS

- A. Immediately report to Owner all PCB spills on the ground or in the water, PCB spills in drip pans, and PCB leaks.
- B. Control Area: Rope off area around edges of PCB leaks and spills and post "PCB Spill Authorized Personnel Only" caution sign. Immediately transfer leaking items to drip pan or other container.
- C. Cleanup: Comply with 40 CFR 761, Subpart G.
 - 1. Initiate cleanup of spills as soon as possible, but no later than 48 hours of its discovery.
 - 2. Require personnel to wear specified PPE, unless determined not required by CIH.

3. If misting, elevated temperatures, or open flames are present, or if spill is situated in a confined space, notify Owner.
 4. Mop up liquid with rags or other conventional absorbent.
 5. Treat spent absorbent as solid PCB waste.
- D. Records and Certification: Document cleanup with records of decontamination in accordance with 40 CFR 761, Section 125, Requirements for PCB Spill Cleanup; provide certification of decontamination.
- E. Sampling: Perform post cleanup sampling as required by 40 CFR 761, Section 130, Sampling Requirements.
- F. Do not remove boundaries of PCB control area until site is determined satisfactorily clean by Owner.

3.06 TEMPORARY STORAGE PRIOR TO DISPOSAL

- A. Storage Site: Obtain Owner's approval in advance of areas, spaces, rooms, and buildings used to store toxic substances prior to disposal off-site; storage sites must comply with the following criteria without exception:
1. Adequate roof and walls to prevent rainwater from reaching stored toxic substances.
 2. Adequate floor that has continuous curbing with minimum 6 inch high curb, with containment volume equal to at least two times internal volume of largest toxic substance article or container stored therein or 25 percent of total internal volume of all toxic substance containing equipment or containers stored therein, whichever is greater.
 3. No drain valves, floor drains, expansion joints, sewer lines, or other openings that would permit liquids to flow from curbed area.
 4. Floors and curbing constructed of continuous smooth and impervious materials, such as Portland cement, concrete, or steel, to prevent or minimize penetrations of toxic substances.
 5. Not located at a site that is below the 100-year flood water elevation.
 6. Posted with specified Caution Sign.
- B. Store PCBs, PCB articles, and PCB-contaminated items in specified containers.
1. Label waste containers with the following:
 - a. "Solid (or Liquid) Waste Polychlorinated Biphenyls."
 - b. Specified PCB Caution Label.
 - c. Date item was placed in storage and name of generator.
 2. Label PCB articles and PCB-contaminated items with the following:
 - a. Specified PCB Caution Label.
 - b. Date item was placed in storage and name of generator.
- C. Label mercury-containing lamp waste in accordance with 40 CFR 273. Affix labels to all lighting waste containers.

3.07 CLEANING

- A. Clean up and containerize wastes daily.
- B. Maintain surfaces of Control Areas free of accumulations of toxic substances. Restrict spread of dust and debris; keep waste from being distributed over work area.
- C. Do not remove Control Area boundaries or warning signs prior to Owner's approval.

D. Reclean areas showing residual toxic substances.

3.08 DISPOSAL BY CONTRACTOR

- A. Comply with disposal requirements and procedures specified in 40 CFR 761 ; deliver toxic substance waste to a disposal facility having required permits.
1. Do not accept toxic substance waste unless it is accompanied by a manifest signed by Owner.
 2. Before transporting toxic substance waste, sign and date manifest acknowledging acceptance of the waste from Owner.
 3. Return a signed copy to Owner before leaving project site.
 4. Ensure that manifest accompanies waste at all times.
 5. Submit transporter certification of notification to EPA of their toxic substance waste activities.
- B. Payment will not be made until Certificate of Disposal has been furnished to Owner.
- C. Certificate of Disposal: Submit to Owner within 30 days of date that disposal of waste identified on manifest was completed; include on the certificate:
1. The identity of disposal facility, by name, address, and EPA identification number.
 2. The identity of waste affected by Certificate of Disposal including reference to manifest number for the shipment.
 3. Statement certifying the fact of disposal of the identified waste, including date(s) of disposal, and identifying disposal process used.
 4. Certification as defined in 40 CFR 761, Section 3.

END OF SECTION

SECTION 23 07 13 DUCT INSULATION

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Duct liner.

1.02 REFERENCE STANDARDS

- A. ASTM C411 - Standard Test Method for Hot-Surface Performance of High-Temperature Thermal Insulation.
- B. ASTM C916 - Standard Specification for Adhesives for Duct Thermal Insulation; 2020.
- C. ASTM C1071 - Standard Specification for Fibrous Glass Duct Lining Insulation (Thermal and Sound Absorbing Material); 2019.
- D. ASTM E84 - Standard Test Method for Surface Burning Characteristics of Building Materials; 2023c.
- E. ASTM G21 - Standard Practice for Determining Resistance of Synthetic Polymeric Materials to Fungi; 2015, with Editorial Revision (2021).
- F. SMACNA (DCS) - HVAC Duct Construction Standards Metal and Flexible; 2020.
- G. UL 723 - Standard for Test for Surface Burning Characteristics of Building Materials; Current Edition, Including All Revisions.

1.03 SUBMITTALS

- A. See Section 01 30 00 - Administrative Requirements for submittal procedures.
- B. Product Data: Provide product description, thermal characteristics, list of materials and thickness for each service, and locations.
- C. Manufacturer's Instructions: Indicate installation procedures necessary to ensure acceptable workmanship and that installation standards will be achieved.

1.04 QUALITY ASSURANCE

- A. Applicator Qualifications: Company specializing in performing the type of work specified in this section, with minimum three years of experience and approved by manufacturer.

1.05 DELIVERY, STORAGE, AND HANDLING

- A. Accept materials on site in original factory packaging, labelled with manufacturer's identification, including product density and thickness.
- B. Protect insulation from weather and construction traffic, dirt, water, chemical, and mechanical damage, by storing in original wrapping.

1.06 FIELD CONDITIONS

- A. Maintain ambient temperatures and conditions required by manufacturers of adhesives, mastics, and insulation cements.

- B. Maintain temperature during and after installation for minimum period of 24 hours.

PART 2 PRODUCTS

2.01 REGULATORY REQUIREMENTS

- A. Surface Burning Characteristics: Flame spread index/Smoke developed index of 25/50, maximum, when tested in accordance with ASTM E84, UL 723, ASTM E84, or UL 723.
- B. Insulation minimum thickness shall meet or exceed requirements as listed in International Energy Conservation Code, 2021.

2.02 DUCT LINER

- A. Manufacturers:
 - 1. CertainTeed Corporation.
 - 2. Johns Manville Corporation.
 - 3. Knauf Insulation.
 - 4. Owens Corning Corporation.
- B. Glass Fiber Insulation: Non-corrosive, incombustible glass fiber complying with ASTM C1071; flexible blanket; impregnated surface and edges coated with poly vinyl acetate polymer, acrylic polymer, or black composite.
 - 1. Fungal Resistance: No growth when tested according to ASTM G21.
 - 2. Apparent Thermal Conductivity: Maximum of 0.31 at 75 degrees F.
 - 3. Service Temperature: Up to 250 degrees F.
 - 4. Rated Velocity on Coated Air Side for Air Erosion: 5,000 fpm, minimum.
 - 5. Minimum Noise Reduction Coefficients:
 - a. 1/2 inch Thickness: 0.30.
- C. Adhesive: Waterproof, fire-retardant type, ASTM C916.
- D. Liner Fasteners: Galvanized steel, self-adhesive pad with integral head.

PART 3 EXECUTION

3.01 EXAMINATION

- A. Test ductwork for design pressure prior to applying insulation materials.
- B. Verify that surfaces are clean, foreign material removed, and dry.

3.02 INSTALLATION

- A. Install in accordance with manufacturer's instructions.
- B. Install in accordance with NAIMA National Insulation Standards.
- C. Duct and Plenum Liner Application:
 - 1. Adhere insulation with adhesive for 90 percent coverage.
 - 2. Secure insulation with mechanical liner fasteners. Refer to SMACNA (DCS) for spacing.
 - 3. Seal and smooth joints. Seal and coat transverse joints.
 - 4. Seal liner surface penetrations with adhesive.

5. Duct dimensions indicated are net inside dimensions required for airflow. Increase duct size to allow for insulation thickness.

3.03 SCHEDULES

- A. Return Ducts with sound requirement:
 1. Duct Liner: 1/2 inches thick.

END OF SECTION

**SECTION 23 31 00
HVAC DUCTS AND CASINGS**

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Metal ducts.

1.02 RELATED REQUIREMENTS

- A. Section 23 07 13 - Duct Insulation: Duct liner.
- B. Section 23 37 00 - Air Outlets and Inlets: Fabric air distribution devices.

1.03 REFERENCE STANDARDS

- A. ASTM A653/A653M - Standard Specification for Steel Sheet, Zinc-Coated (Galvanized) or Zinc-Iron Alloy-Coated (Galvannealed) by the Hot-Dip Process; 2023.
- B. NFPA 90A - Standard for the Installation of Air-Conditioning and Ventilating Systems; 2024.
- C. SMACNA (DCS) - HVAC Duct Construction Standards Metal and Flexible; 2020.
- D. UL 181 - Standard for Factory-Made Air Ducts and Air Connectors; Current Edition, Including All Revisions.

1.04 REGULATORY REQUIREMENTS

- A. Construct ductwork to NFPA 90A standards.

1.05 FIELD CONDITIONS

- A. Do not install duct sealants when temperatures are less than those recommended by sealant manufacturers.
- B. Maintain temperatures within acceptable range during and after installation of duct sealants.

PART 2 PRODUCTS

2.01 METAL DUCTS

- A. Material Requirements:
 - 1. Galvanized Steel: Hot-dipped galvanized steel sheet, ASTM A653/A653M FS Type B, with G60/Z180 coating.

PART 3 EXECUTION

3.01 INSTALLATION

- A. Install, support, and seal ducts in accordance with SMACNA (DCS).
- B. Duct sizes indicated are precise inside dimensions. For lined ducts, maintain sizes inside lining.
- C. Duct sizes indicated shall be of sizes indicated. However, necessary changes in shape offsets or crossovers to clear piping, lighting, building construction obstructions, etc. shall be made without additional cost.

D. Locate ducts with sufficient space around equipment to allow normal operating and maintenance activities.

END OF SECTION

SECTION 23 37 00
AIR OUTLETS AND INLETS

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Registers/grilles:
 - 1. Ceiling-mounted, egg crate exhaust and return register/grilles.

1.02 REFERENCE STANDARDS

- A. NFPA 90A - Standard for the Installation of Air-Conditioning and Ventilating Systems; 2024.

1.03 SUBMITTALS

- A. See Section 01 30 00 - Administrative Requirements for submittal procedures.
- B. Product Data: Provide data for equipment required for this project. Review outlets and inlets as to size, finish, and type of mounting prior to submission. Submit schedule of outlets and inlets showing type, size, location, application, and noise level.

1.04 QUALITY ASSURANCE

- A. Manufacturer Qualifications: Company specializing in manufacturing the type of products specified in this section, with minimum three years of documented experience.

PART 2 PRODUCTS

2.01 CEILING EGG CRATE EXHAUST AND RETURN GRILLES

- A. Manufacturers:
 - 1. Titus; Model 50F.
 - 2. Price; Model 80.
 - 3. Nailor; Model 51EC.
- B. Type: Egg crate style face consisting of 1/2 by 1/2 by 1/2 inch grid core.
- C. Fabrication: Grid core consists of aluminum with baked enamel finish. Color = white.
- D. Frame: Channel lay-in frame for suspended grid ceilings.

PART 3 EXECUTION

3.01 INSTALLATION

- A. Install in accordance with manufacturer's instructions.
- B. Check location of outlets and inlets and make necessary adjustments in position to comply with architectural features, symmetry, and lighting arrangement.
- C. Install diffusers to ductwork with air tight connection.

END OF SECTION

SECTION 26 05 00
BASIC ELECTRICAL REQUIREMENTS

PART 1 GENERAL

1.01 RELATED DOCUMENTS

- A. Drawings and general provisions of Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.02 SECTION INCLUDES

- A. Basic Electrical Requirements specifically applicable to Division 26 Sections, in addition to Division 01 - General Requirements.

1.03 REGULATORY REQUIREMENTS

- A. Provide all materials and labor in conformance with the following codes and standards:
 - 1. Main Campus
 - a. City of Joliet, IL - Code of Ordinances.
 - b. ANSI/NFPA 70 - National Electrical Code 2014 Edition as adopted and Amended by City of Joliet, Illinois.
 - c. IBC International Building Code, 2015 Edition, with local amendments.
 - 2. Romeoville Campus
 - a. Village of Joliet, IL - Code of Ordinances.
 - b. ANSI/NFPA 70 - National Electrical Code 2020 Edition as adopted and Amended by Village of Romeoville, Illinois.
 - c. IBC International Building Code, 2021 Edition, with local amendments.
 - 3. IECC International Energy Conservation Code, 2021 Edition with local amendments.
 - 4. ADA-AG - American with Disabilities Act - Accessibility Guidelines.
 - 5. Illinois Accessibility Code, 1997 Edition (Illinois Administrative Code, Title 71, Chapter I, Subchapter b, Part 400).
 - 6. Install electrical Work in accordance with the NECA Standard of Installation.

1.04 DELIVERY, STORAGE AND HANDLING

- A. Store and protect all materials as specified under the provisions of Section 01 60 00 and as specified herein.
- B. Deliver products to the project properly identified with names, model numbers, types, grades, compliance labels, and other information needed for identification.
- C. Ship products to the job site in their original packaging. Receive and store products in a suitable manner to prevent damage or deterioration. Keep equipment upright at all times.
- D. Investigate the spaces through which equipment must pass to reach its final destination. Coordinate with the manufacturer to arrange delivery at the proper stage of construction and to provide shipping splits where necessary.

1.05 PROJECT/SITE CONDITIONS

- A. Install work in locations shown on Drawings, unless prevented by Project conditions. Drawings have omitted certain branch circuitry in areas for ease of reading. All branch circuitry is to be provided by Contractor.
- B. Prepare drawings showing proposed rearrangement of Work to meet Project conditions, including changes to Work specified in other Sections. Obtain permission from Architect/Engineer before proceeding as specified under modification procedures.

1.06 QUALITY ASSURANCE

- A. Provide Work as required for a complete and operational electrical installation.
- B. All products shall be designed, manufactured, and tested in accordance with industry standards. Standards, organizations, and their abbreviations as used hereafter, include the following:
 - 1. American National Standards Institute, Inc (ANSI).
 - 2. American Society for Testing and Materials (ASTM).
 - 3. National Electrical Manufacturers Association (NEMA).
 - 4. Underwriters Laboratories, Inc. (UL).
- C. Install all Work in accordance with the NECA Standard of Installation.

1.07 PROJECT MANAGEMENT AND COORDINATION

- A. Proper project management and coordination is critical for a successful project. Manage and coordinate the Work with all other trades. Reliance on the Drawings and Specifications only for exact project requirements is insufficient for proper coordination.

PART 2 PRODUCTS - NOT USED

PART 3 EXECUTION - NOT USED

END OF SECTION

SECTION 26 05 05
SELECTIVE DEMOLITION FOR ELECTRICAL

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Electrical demolition.

1.02 SUMMARY

- A. Section Includes:
 - 1. Electrical demolition: Remove electrical systems shown on drawings.

PART 2 PRODUCTS

2.01 MATERIALS AND EQUIPMENT

- A. Materials and equipment for patching and extending work: As specified in individual sections.

PART 3 EXECUTION

3.01 EXAMINATION

- A. Verify field measurements and circuiting arrangements are as indicated.
- B. Verify that abandoned wiring and equipment serve only abandoned facilities.
- C. Demolition drawings are based on casual field observation and existing record documents.
- D. Report discrepancies to Owner before disturbing existing installation.
- E. Beginning of demolition means installer accepts existing conditions.
- F. Demolition Drawings are based on casual field observation and are intended to identify the limits of the construction site. Remove all electrical systems in their entirety in proper sequence with the Work.

3.02 PREPARATION

- A. Disconnect electrical systems in walls, floors, and ceilings to be removed.
- B. Coordinate utility service outages with utility company.
- C. Provide temporary wiring and connections to maintain existing systems in service during construction. When work must be performed on energized equipment or circuits, use personnel experienced in such operations.
- D. Existing Electrical Service: Maintain existing system in service. Disable system only to make switchovers and connections. Minimize outage duration.
 - 1. Make temporary connections to maintain service in areas adjacent to work area.

3.03 DEMOLITION AND EXTENSION OF EXISTING ELECTRICAL WORK

- A. Perform work for removal and disposal of equipment and materials containing toxic substances regulated under the Federal Toxic Substances Control Act (TSCA) in accordance with applicable federal, state, and local regulations. Applicable equipment and materials include, but are not limited to:

1. PCB- and DEHP-containing lighting ballasts.
 2. Mercury-containing lamps and tubes, including fluorescent lamps, high intensity discharge (HID), arc lamps, ultra-violet, high pressure sodium, mercury vapor, ignitron tubes, neon, and incandescent.
- B. Remove, relocate, and extend existing installations to accommodate new construction.
 - C. Remove abandoned wiring to source of supply.
 - D. Remove exposed abandoned conduit, including abandoned conduit above accessible ceiling finishes. Cut conduit flush with walls and floors, and patch surfaces.
 - E. Disconnect abandoned outlets and remove devices. Remove abandoned outlets if conduit servicing them is abandoned and removed. Provide blank cover for abandoned outlets that are not removed.
 - F. Disconnect and remove electrical devices and equipment serving utilization equipment that has been removed.
 - G. Disconnect and remove abandoned luminaires. Remove brackets, stems, hangers, and other accessories.
 - H. Repair adjacent construction and finishes damaged during demolition and extension work.
 - I. Maintain access to existing electrical installations that remain active. Modify installation or provide access panel as appropriate.
 - J. Extend existing installations using materials and methods compatible with existing electrical installations, or as specified.
 - K. Properly dispose of all ballast to approved ballast recycler. Do not land fill ballasts.

3.04 CLEANING AND REPAIR

- A. Clean and repair existing materials and equipment that remain or that are to be reused.

END OF SECTION

SECTION 26 05 19
LOW-VOLTAGE ELECTRICAL POWER CONDUCTORS AND CABLES

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Single conductor building wire.
- B. Metal-clad cable.
- C. Wiring connectors.
- D. Electrical tape.
- E. Heat shrink tubing.
- F. Wire pulling lubricant.
- G. Cable ties.
- H. Firestop sleeves.

1.02 REFERENCE STANDARDS

- A. ASTM B3 - Standard Specification for Soft or Annealed Copper Wire; 2013 (Reapproved 2018).
- B. ASTM B8 - Standard Specification for Concentric-Lay-Stranded Copper Conductors, Hard, Medium-Hard, or Soft; 2023.
- C. ASTM B33 - Standard Specification for Tin-Coated Soft or Annealed Copper Wire for Electrical Purposes; 2010, with Editorial Revision (2020).
- D. ASTM B787/B787M - Standard Specification for 19 Wire Combination Unilay-Stranded Copper Conductors for Subsequent Insulation; 2004 (Reapproved 2020).
- E. ASTM D3005 - Standard Specification for Low-Temperature Resistant Vinyl Chloride Plastic Pressure-Sensitive Electrical Insulating Tape; 2017.
- F. ASTM D4388 - Standard Specification for Nonmetallic Semi-Conducting and Electrically Insulating Rubber Tapes; 2020.
- G. NECA 1 - Standard for Good Workmanship in Electrical Construction; 2015.
- H. NECA 120 - Standard for Installing Armored Cable (AC) and Type Metal-Clad (MC) Cable; 2018.
- I. NEMA WC 70 - Power Cables Rated 2000 Volts or Less for the Distribution of Electrical Energy; 2021.
- J. NFPA 70 - National Electrical Code; Most Recent Edition Adopted by Authority Having Jurisdiction, Including All Applicable Amendments and Supplements.
- K. UL 44 - Thermoset-Insulated Wires and Cables; Current Edition, Including All Revisions.
- L. UL 83 - Thermoplastic-Insulated Wires and Cables; Current Edition, Including All Revisions.
- M. UL 267 - Outline of Investigation for Wire-Pulling Compounds; Current Edition, Including All Revisions.

- N. UL 486A-486B - Wire Connectors; Current Edition, Including All Revisions.
- O. UL 486C - Splicing Wire Connectors; Current Edition, Including All Revisions.
- P. UL 486D - Sealed Wire Connector Systems; Current Edition, Including All Revisions.
- Q. UL 510 - Polyvinyl Chloride, Polyethylene, and Rubber Insulating Tape; Current Edition, Including All Revisions.
- R. UL 1569 - Metal-Clad Cables; Current Edition, Including All Revisions.

1.03 ADMINISTRATIVE REQUIREMENTS

- A. Coordination:
 - 1. Coordinate sizes of raceways, boxes, and equipment enclosures installed under other sections with the actual conductors to be installed, including adjustments for conductor sizes increased for voltage drop.
 - 2. Coordinate with electrical equipment installed under other sections to provide terminations suitable for use with the conductors to be installed.
 - 3. Notify Architect/Engineer of any conflicts with or deviations from Contract Documents. Obtain direction before proceeding with work.

1.04 QUALITY ASSURANCE

- A. Comply with requirements of NFPA 70.

1.05 DELIVERY, STORAGE, AND HANDLING

- A. Receive, inspect, handle, and store conductors and cables in accordance with manufacturer's instructions.

PART 2 PRODUCTS

2.01 CONDUCTOR AND CABLE APPLICATIONS

- A. Do not use conductors and cables for applications other than as permitted by NFPA 70 and product listing.
- B. Provide single conductor building wire installed in suitable raceway unless otherwise indicated, permitted, or required.
- C. Nonmetallic-sheathed cable is not permitted.
- D. Underground feeder and branch-circuit cable is not permitted.
- E. Service entrance cable is not permitted.
- F. Armored cable is not permitted.
- G. Metal-clad cable is permitted only as follows:
 - 1. Where not otherwise restricted, may be used:
 - a. Where concealed above accessible ceilings for final connections from junction boxes to luminaires.
 - 1) Maximum Length: 6 feet.

- b. Where concealed in hollow stud walls, above accessible ceilings, and under raised floors for branch circuits up to 20 A.
- 2. In addition to other applicable restrictions, may not be used:
 - a. Where exposed to damage.
 - b. For damp, wet, or corrosive locations, unless provided with a PVC jacket listed as suitable for those locations.

2.02 CONDUCTOR AND CABLE GENERAL REQUIREMENTS

- A. Provide products that comply with requirements of NFPA 70.
- B. Provide products listed, classified, and labeled as suitable for the purpose intended.
- C. Unless specifically indicated to be excluded, provide all required conduit, boxes, wiring, connectors, etc. as required for a complete operating system.
- D. Comply with NEMA WC 70.
- E. Thermoplastic-Insulated Conductors and Cables: Listed and labeled as complying with UL 83.
- F. Thermoset-Insulated Conductors and Cables: Listed and labeled as complying with UL 44.
- G. Conductors for Grounding and Bonding: Also comply with Section 26 05 26.
- H. Conductor Material:
 - 1. Provide copper conductors only. Aluminum conductors are not acceptable for this project. Conductor sizes indicated are based on copper.
 - 2. Copper Conductors: Soft drawn annealed, 98 percent conductivity, uncoated copper conductors complying with ASTM B3, ASTM B8, or ASTM B787/B787M unless otherwise indicated.
 - 3. Tinned Copper Conductors: Comply with ASTM B33.
- I. Minimum Conductor Size:
 - 1. Branch Circuits: 12 AWG.
 - a. Exceptions:
 - 1) 20 A, 120 V circuits longer than 75 feet: 10 AWG, for voltage drop.
 - 2) 20 A, 120 V circuits longer than 150 feet: 8 AWG, for voltage drop.
 - 3) 20 A, 277 V circuits longer than 150 feet: 10 AWG, for voltage drop.
- J. Conductor Color Coding:
 - 1. Color code conductors as indicated unless otherwise required by the authority having jurisdiction. Maintain consistent color coding throughout project.
 - 2. Color Coding Method: Integrally colored insulation.
 - 3. Color Code:
 - a. 480Y/277 V, 3 Phase, 4 Wire System:
 - 1) Phase A: Brown.
 - 2) Phase B: Orange.
 - 3) Phase C: Yellow.
 - 4) Neutral/Grounded: Gray.
 - b. 208Y/120 V, 3 Phase, 4 Wire System:
 - 1) Phase A: Black.
 - 2) Phase B: Red.

- 3) Phase C: Blue.
- 4) Neutral/Grounded: White.
- c. Equipment Ground, All Systems: Green.
- d. For modifications or additions to existing wiring systems, comply with existing color code when existing code complies with NFPA 70 and is approved by the authority having jurisdiction.

2.03 SINGLE CONDUCTOR BUILDING WIRE

- A. Manufacturers:
 - 1. Copper Building Wire:
 - a. Cerro Wire LLC: www.cerrowire.com/#sle.
 - b. Encore Wire Corporation: www.encorewire.com/#sle.
 - c. Southwire Company: www.southwire.com/#sle.
- B. Description: Single conductor insulated wire.
- C. Conductor Stranding:
 - 1. Feeders and Branch Circuits:
 - a. Size 10 AWG and Smaller: Solid.
 - b. Size 8 AWG and Larger: Stranded.
- D. Insulation Voltage Rating: 600 V.
- E. Insulation:
 - 1. Copper Building Wire: Type THHN/THWN or THHN/THWN-2, except as indicated below.

2.04 METAL-CLAD CABLE

- A. Manufacturers:
- B. Description: NFPA 70, Type MC cable listed and labeled as complying with UL 1569, and listed for use in classified firestop systems to be used.
- C. Conductor Stranding:
 - 1. Size 10 AWG and Smaller: Solid.
 - 2. Size 8 AWG and Larger: Stranded.
- D. Insulation Voltage Rating: 600 V.
- E. Insulation: Type THHN, THHN/THWN, or THHN/THWN-2.
- F. Grounding: Full-size integral equipment grounding conductor.
- G. Armor: Steel, interlocked tape.
- H. Provide PVC jacket applied over cable armor where indicated or required for environment of installed location.

2.05 WIRING CONNECTORS

- A. Description: Wiring connectors appropriate for the application, suitable for use with the conductors to be connected, and listed as complying with UL 486A-486B or UL 486C as applicable.
- B. Wiring Connectors for Splices and Taps:

1. Copper Conductors Size 8 AWG and Smaller: Use twist-on insulated spring connectors.
 2. Copper Conductors Size 6 AWG and Larger: Use mechanical connectors or compression connectors.
- C. Twist-on Insulated Spring Connectors: Rated 600 V, 221 degrees F for standard applications and 302 degrees F for high temperature applications; pre-filled with sealant and listed as complying with UL 486D for damp and wet locations.
- D. Mechanical Connectors: Provide bolted type or set-screw type.
- E. Compression Connectors: Provide circumferential type or hex type crimp configuration.

2.06 ACCESSORIES

- A. Electrical Tape:
1. Vinyl Color Coding Electrical Tape: Integrally colored to match color code indicated; listed as complying with UL 510; minimum thickness of 7 mil; resistant to abrasion, corrosion, and sunlight; suitable for continuous temperature environment up to 221 degrees F.
 2. Vinyl Insulating Electrical Tape: Complying with ASTM D3005 and listed as complying with UL 510; minimum thickness of 7 mil; resistant to abrasion, corrosion, and sunlight; conformable for application down to 0 degrees F and suitable for continuous temperature environment up to 221 degrees F.
 3. Rubber Splicing Electrical Tape: Ethylene Propylene Rubber (EPR) tape, complying with ASTM D4388; minimum thickness of 30 mil; suitable for continuous temperature environment up to 194 degrees F and short-term 266 degrees F overload service.
 4. Electrical Filler Tape: Rubber-based insulating moldable putty, minimum thickness of 125 mil; suitable for continuous temperature environment up to 176 degrees F.
- B. Heat Shrink Tubing: Heavy-wall, split-resistant, with factory-applied adhesive; rated 600 V; suitable for direct burial applications; listed as complying with UL 486D.
- C. Wire Pulling Lubricant:
1. Listed and labeled as complying with UL 267.
 1. Suitable for use at installation temperature.
 1. Suitable for use with conductors/cables and associated insulation/jackets to be installed.
- D. Firestop Sleeves: Listed; provide as required to preserve fire resistance rating of building elements.

PART 3 EXECUTION

3.01 EXAMINATION

- A. Verify that work likely to damage wire and cable has been completed.
- B. Verify that raceways, boxes, and equipment enclosures are installed and are properly sized to accommodate conductors and cables in accordance with NFPA 70.
- C. Verify that field measurements are as indicated.
- D. Verify that conditions are satisfactory for installation prior to starting work.

3.02 PREPARATION

- A. Clean raceways thoroughly to remove foreign materials before installing conductors and cables.

3.03 INSTALLATION

- A. Circuiting Requirements:
 - 1. Unless dimensioned, circuit routing indicated is diagrammatic.
 - 2. When circuit destination is indicated without specific routing, determine exact routing required.
 - 3. Arrange circuiting to minimize splices.
 - 4. Include circuit lengths required to install connected devices within 10 ft of location indicated.
- B. Install products in accordance with manufacturer's instructions.
- C. Perform work in accordance with NECA 1 (general workmanship).
- D. Install metal-clad cable (Type MC) in accordance with NECA 120.
- E. Installation in Raceway:
 - 1. Tape ends of conductors and cables to prevent infiltration of moisture and other contaminants.
 - 2. Pull all conductors and cables together into raceway at same time.
 - 3. Do not damage conductors and cables or exceed manufacturer's recommended maximum pulling tension and sidewall pressure.
 - 4. Use suitable wire pulling lubricant where necessary, except when lubricant is not recommended by the manufacturer.
- F. Paralleled Conductors: Install conductors of the same length and terminate in the same manner.
- G. Secure and support conductors and cables in accordance with NFPA 70 using suitable supports and methods approved by the authority having jurisdiction. Provide independent support from building structure. Do not provide support from raceways, piping, ductwork, or other systems.
- H. Terminate cables using suitable fittings.
 - 1. Metal-Clad Cable (Type MC):
 - a. Use listed fittings.
 - b. Cut cable armor only using specialized tools to prevent damaging conductors or insulation. Do not use hacksaw or wire cutters to cut armor.
- I. Install conductors with a minimum of 12 inches of slack at each outlet.
- J. Neatly train and bundle conductors inside boxes, wireways, panelboards and other equipment enclosures.
- K. Group or otherwise identify neutral/grounded conductors with associated ungrounded conductors inside enclosures in accordance with NFPA 70.
- L. Make wiring connections using specified wiring connectors.
 - 1. Make splices and taps only in accessible boxes. Do not pull splices into raceways or make splices in conduit bodies or wiring gutters.
 - 2. Remove appropriate amount of conductor insulation for making connections without cutting, nicking or damaging conductors.
 - 3. Do not remove conductor strands to facilitate insertion into connector.

4. Clean contact surfaces on conductors and connectors to suitable remove corrosion, oxides, and other contaminates. Do not use wire brush on plated connector surfaces.
 5. Mechanical Connectors: Secure connections according to manufacturer's recommended torque settings.
 6. Compression Connectors: Secure connections using manufacturer's recommended tools and dies.
- M. Insulate splices and taps that are made with uninsulated connectors using methods suitable for the application, with insulation and mechanical strength at least equivalent to unspliced conductors.
1. Dry Locations: Use insulating covers specifically designed for the connectors, electrical tape, or heat shrink tubing.
 - a. For taped connections, first apply adequate amount of rubber splicing electrical tape or electrical filler tape, followed by outer covering of vinyl insulating electrical tape.
- N. Insulate ends of spare conductors using vinyl insulating electrical tape.
- O. Install firestopping to preserve fire resistance rating of partitions and other elements.
- P. Unless specifically indicated to be excluded, provide final connections to all equipment and devices, including those furnished by others, as required for a complete operating system.

END OF SECTION

SECTION 26 05 26
GROUNDING AND BONDING FOR ELECTRICAL SYSTEMS

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Grounding and bonding requirements.
- B. Conductors for grounding and bonding.
- C. Connectors for grounding and bonding.

1.02 RELATED REQUIREMENTS

- A. Section 26 05 19 - Low-Voltage Electrical Power Conductors and Cables: Additional requirements for conductors for grounding and bonding, including conductor color coding.
- B. Section 26 05 53 - Identification for Electrical Systems: Identification products and requirements.

1.03 REFERENCE STANDARDS

- A. IEEE 81 - IEEE Guide for Measuring Earth Resistivity, Ground Impedance, and Earth Surface Potentials of a Grounding System; 2012.
- B. NECA 1 - Standard for Good Workmanship in Electrical Construction; 2015.
- C. NEMA GR 1 - Grounding Rod Electrodes and Grounding Rod Electrode Couplings; 2022.
- D. NETA ATS - Standard For Acceptance Testing Specifications For Electrical Power Equipment And Systems; 2021.
- E. NFPA 70 - National Electrical Code; Most Recent Edition Adopted by Authority Having Jurisdiction, Including All Applicable Amendments and Supplements.
- F. UL 467 - Grounding and Bonding Equipment; Current Edition, Including All Revisions.

1.04 ADMINISTRATIVE REQUIREMENTS

- A. Coordination:
 - 1. Notify Architect/Engineer of any conflicts with or deviations from Contract Documents. Obtain direction before proceeding with work.
- B. Sequencing:
 - 1. Do not install ground rod electrodes until final backfill and compaction is complete.

1.05 QUALITY ASSURANCE

- A. Comply with requirements of NFPA 70.
- B. Product Listing Organization Qualifications: An organization recognized by OSHA as a Nationally Recognized Testing Laboratory (NRTL) and acceptable to authorities having jurisdiction.

1.06 DELIVERY, STORAGE, AND HANDLING

- A. Receive, inspect, handle, and store products in accordance with manufacturer's instructions.

PART 2 PRODUCTS

2.01 GROUNDING AND BONDING REQUIREMENTS

- A. Existing Work: Where existing grounding and bonding system components are indicated to be reused, they may be reused only where they are free from corrosion, integrity and continuity are verified, and where acceptable to the authority having jurisdiction.
- B. Do not use products for applications other than as permitted by NFPA 70 and product listing.
- C. Unless specifically indicated to be excluded, provide all required components, conductors, connectors, conduit, boxes, fittings, supports, accessories, etc. as necessary for a complete grounding and bonding system.
- D. Where conductor size is not indicated, size to comply with NFPA 70 but not less than applicable minimum size requirements specified.
- E. Grounding System Resistance:
 - 1. Achieve specified grounding system resistance under normally dry conditions unless otherwise approved by Architect/Engineer. Precipitation within the previous 48 hours does not constitute normally dry conditions.
 - 2. Grounding Electrode System: Not greater than 5 ohms to ground, when tested according to IEEE 81 using "fall-of-potential" method.

2.02 GROUNDING AND BONDING COMPONENTS

- A. General Requirements:
 - 1. Provide products listed, classified, and labeled as suitable for the purpose intended.
 - 2. Provide products listed and labeled as complying with UL 467 where applicable.
- B. Conductors for Grounding and Bonding, in Addition to Requirements of Section 26 05 26:
 - 1. Use insulated copper conductors unless otherwise indicated.
- C. Connectors for Grounding and Bonding:
 - 1. Description: Connectors appropriate for the application and suitable for the conductors and items to be connected; listed and labeled as complying with UL 467.
 - a. Clamps: Bronze.
 - 2. Unless otherwise indicated, use exothermic welded connections for underground, concealed and other inaccessible connections.
 - 3. Unless otherwise indicated, use mechanical connectors, compression connectors, or exothermic welded connections for accessible connections.
 - 4. Manufacturers - Mechanical and Compression Connectors:
 - a. Harger Lightning & Grounding: www.harger.com/#sle.
 - b. Thomas & Betts Corporation: www.tnb.com/#sle.
 - c. Substitutions: See Section 01 60 00 - Product Requirements.
 - 5. Manufacturers - Exothermic Welded Connections:
 - a. Cadweld, a brand of Erico International Corporation: www.erico.com/#sle.
 - b. thermOweld, subsidiary of Continental Industries; division of Burndy LLC: www.thermoweld.com/#sle.
 - c. Substitutions: See Section 01 60 00 - Product Requirements.

PART 3 EXECUTION

3.01 EXAMINATION

- A. Verify that work likely to damage grounding and bonding system components has been completed.
- B. Verify that field measurements are as indicated.
- C. Verify that conditions are satisfactory for installation prior to starting work.

3.02 INSTALLATION

- A. Install products in accordance with manufacturer's instructions.
- B. Perform work in accordance with NECA 1 (general workmanship).
- C. Make grounding and bonding connections using specified connectors.
 - 1. Remove appropriate amount of conductor insulation for making connections without cutting, nicking or damaging conductors. Do not remove conductor strands to facilitate insertion into connector.
 - 2. Remove nonconductive paint, enamel, or similar coating at threads, contact points, and contact surfaces.
 - 3. Exothermic Welds: Make connections using molds and weld material suitable for the items to be connected in accordance with manufacturer's recommendations.
 - 4. Mechanical Connectors: Secure connections according to manufacturer's recommended torque settings.
 - 5. Compression Connectors: Secure connections using manufacturer's recommended tools and dies.
- D. Identify grounding and bonding system components in accordance with Section 26 05 53.

3.03 FIELD QUALITY CONTROL

- A. Inspect and test in accordance with NETA ATS except Section 4.
- B. Perform inspections and tests listed in NETA ATS, Section 7.13.
- C. Perform ground electrode resistance tests under normally dry conditions. Precipitation within the previous 48 hours does not constitute normally dry conditions.
- D. Investigate and correct deficiencies where measured ground resistances do not comply with specified requirements.
- E. Inspect grounding and bonding system conductors and connections for tightness and proper installation.
- F. Measure ground resistance from system neutral connection at service entrance to convenient ground reference point by passing minimum current of 10 amperes DC and measuring voltage drop. Maximum resistance: 5 ohms.

END OF SECTION

SECTION 26 05 29
HANGERS AND SUPPORTS FOR ELECTRICAL SYSTEMS

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Support and attachment requirements and components for equipment, conduit, cable, boxes, and other electrical work.

1.02 RELATED REQUIREMENTS

- A. Section 26 05 33.13 - Conduit for Electrical Systems: Additional support and attachment requirements for conduits.
- B. Section 26 05 33.16 - Boxes for Electrical Systems: Additional support and attachment requirements for boxes.
- C. Section 26 51 00 - Interior Luminaires: Additional support and attachment requirements for interior luminaires.

1.03 REFERENCE STANDARDS

- A. ASTM A153/A153M - Standard Specification for Zinc Coating (Hot-Dip) on Iron and Steel Hardware; 2023.
- B. ASTM B633 - Standard Specification for Electrodeposited Coatings of Zinc on Iron and Steel; 2023.
- C. MFMA-4 - Metal Framing Standards Publication; 2004.
- D. NECA 1 - Standard for Good Workmanship in Electrical Construction; 2015.
- E. NFPA 70 - National Electrical Code; Most Recent Edition Adopted by Authority Having Jurisdiction, Including All Applicable Amendments and Supplements.
- F. UL 5B - Strut-Type Channel Raceways and Fittings; Current Edition, Including All Revisions.

1.04 ADMINISTRATIVE REQUIREMENTS

- A. Coordination:
 - 1. Coordinate sizes and arrangement of supports and bases with actual equipment and components to be installed.
 - 2. Coordinate work to provide additional framing and materials required for installation.
 - 3. Coordinate compatibility of support and attachment components with mounting surfaces at installed locations.
 - 4. Coordinate arrangement of supports with ductwork, piping, equipment and other potential conflicts.
 - 5. Notify Architect/Engineer of conflicts with or deviations from Contract Documents. Obtain direction before proceeding with work.

1.05 DELIVERY, STORAGE, AND HANDLING

- A. Receive, inspect, handle, and store products in accordance with manufacturer's instructions.

PART 2 PRODUCTS

2.01 SUPPORT AND ATTACHMENT COMPONENTS

A. General Requirements:

1. Comply with the following. Where requirements differ, comply with most stringent.
 - a. NFPA 70.
 - b. Requirements of authorities having jurisdiction.
2. Provide required hangers, supports, anchors, fasteners, fittings, accessories, and hardware as necessary for complete installation of electrical work.
3. Provide products listed, classified, and labeled as suitable for purpose intended, where applicable.
4. Where support and attachment component types and sizes are not indicated, select in accordance with manufacturer's application criteria as required for load to be supported. Include consideration for vibration, equipment operation, and shock loads where applicable.
 - a. Consider the weight of wire in conduit when selecting products.
5. Do not use products for applications other than as permitted by NFPA 70 and product listing.
6. Do not use wire, chain, perforated pipe strap, or wood for permanent supports unless specifically indicated or permitted.
7. Steel Components: Use corrosion-resistant materials suitable for environment where installed.
 - a. Zinc-Plated Steel: Electroplated in accordance with ASTM B633.
 - b. Galvanized Steel: Hot-dip galvanized after fabrication in accordance with ASTM A123/A123M or ASTM A153/A153M.

B. Conduit and Cable Supports: Straps and clamps suitable for conduit or cable to be supported.

1. Conduit Straps: One-hole or two-hole type; steel or malleable iron.
2. Conduit Clamps: Bolted type unless otherwise indicated.

C. Outlet Box Supports: Hangers and brackets suitable for boxes to be supported.

D. Metal Channel/Strut Framing Systems:

1. Description: Factory-fabricated, continuous-slot, metal channel/strut and associated fittings, accessories, and hardware required for field assembly of supports.
2. Comply with MFMA-4.

E. Hanger Rods: Threaded, zinc-plated steel unless otherwise indicated.

1. Minimum Size, Unless Otherwise Indicated or Required:
 - a. Outlet Boxes: 1/4-inch diameter.
 - b. Luminaires: 1/4-inch diameter.

F. Anchors and Fasteners:

1. Unless otherwise indicated and where not otherwise restricted, use anchor and fastener types indicated for specified applications.
2. Concrete: Use expansion anchors.
3. Solid or Grout-Filled Masonry: Use expansion anchors or screw anchors.
4. Hollow Masonry: Use toggle bolts.
5. Plaster and Gypsum Board Partitions: Use toggle bolts.
6. Steel: Use beam clamps.
7. Sheet Metal: Use sheet metal screws.
8. Wood: Use wood screws.

PART 3 EXECUTION

3.01 EXAMINATION

- A. Verify that field measurements are as indicated.
- B. Verify that mounting surfaces are ready to receive support and attachment components.
- C. Verify that conditions are satisfactory for installation prior to starting work.

3.02 INSTALLATION

- A. Install products in accordance with manufacturer's instructions.
- B. Install hangers and supports in accordance with NECA 1.
- C. Provide independent support from building structure. Do not provide support from piping, ductwork, or other systems.
- D. Unless specifically indicated or approved by Architect/Engineer, do not provide support from suspended ceiling support system or ceiling grid.
- E. Unless specifically indicated or approved by Architect/Engineer, do not provide support from roof deck.
- F. Do not penetrate or otherwise notch or cut structural members without approval of Structural Engineer.
- G. Interior Luminaire Support and Attachment: See Section 26 51 00 for additional requirements.
- H. Secure fasteners in accordance with manufacturer's recommended torque settings.
- I. Remove temporary supports.
- J. Do not use power-actuated anchors.
- K. Do not drill or cut structural members.
- L. Fabricate supports from structural steel or steel channel. Rigidly weld members or use hexagon head bolts to present neat appearance with adequate strength and rigidity. Use spring lock washers under all nuts.

3.03 FIELD QUALITY CONTROL

- A. Inspect support and attachment components for damage and defects.
- B. Repair cuts and abrasions in galvanized finishes using zinc-rich paint recommended by manufacturer. Replace components that exhibit signs of corrosion.
- C. Correct deficiencies and replace damaged or defective support and attachment components.

END OF SECTION

SECTION 26 05 33.13
CONDUIT FOR ELECTRICAL SYSTEMS

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Galvanized steel rigid metal conduit (RMC).
- B. Flexible metal conduit (FMC).
- C. Electrical metallic tubing (EMT).
- D. Conduit fittings.
- E. Accessories.

1.02 RELATED REQUIREMENTS

- A. Section 26 05 26 - Grounding and Bonding for Electrical Systems.
- B. Section 26 05 29 - Hangers and Supports for Electrical Systems.
- C. Section 26 05 53 - Identification for Electrical Systems: Identification products and requirements.

1.03 REFERENCE STANDARDS

- A. ANSI C80.1 - American National Standard for Electrical Rigid Steel Conduit (ERSC); 2020.
- B. ANSI C80.3 - American National Standard for Electrical Metallic Tubing -- Steel (EMT-S); 2020.
- C. NECA 1 - Standard for Good Workmanship in Electrical Construction; 2015.
- D. NECA 101 - Standard for Installing Steel Conduits (Rigid, IMC, EMT); 2020.
- E. NECA 111 - Standard for Installing Nonmetallic Raceways (RNC, ENT, LFNC); 2017.
- F. NEMA FB 1 - Fittings, Cast Metal Boxes, and Conduit Bodies for Conduit, Electrical Metallic Tubing, and Cable; 2014.
- G. NEMA RN 1 - Polyvinyl-Chloride (PVC) Externally Coated Galvanized Rigid Steel Metal Conduit and Intermediate Metal Conduit; 2018.
- H. NEMA TC 2 - Electrical Polyvinyl Chloride (PVC) Conduit; 2020.
- I. NEMA TC 3 - Polyvinyl Chloride (PVC) Fittings for Use with Rigid PVC Conduit and Tubing; 2021.
- J. NFPA 70 - National Electrical Code; Most Recent Edition Adopted by Authority Having Jurisdiction, Including All Applicable Amendments and Supplements.
- K. UL 1 - Flexible Metal Conduit; Current Edition, Including All Revisions.
- L. UL 6 - Electrical Rigid Metal Conduit-Steel; Current Edition, Including All Revisions.
- M. UL 360 - Liquid-Tight Flexible Metal Conduit; Current Edition, Including All Revisions.
- N. UL 514B - Conduit, Tubing, and Cable Fittings; Current Edition, Including All Revisions.

O. UL 651 - Schedule 40, 80, Type EB and A Rigid PVC Conduit and Fittings; Current Edition, Including All Revisions.

P. UL 797 - Electrical Metallic Tubing-Steel; Current Edition, Including All Revisions.

Q. UL 1653 - Electrical Nonmetallic Tubing; Current Edition, Including All Revisions.

1.04 ADMINISTRATIVE REQUIREMENTS

A. Coordination:

1. Coordinate minimum sizes of conduits with the actual conductors to be installed, including adjustments for conductor sizes increased for voltage drop.
2. Coordinate the arrangement of conduits with structural members, ductwork, piping, equipment and other potential conflicts installed under other sections or by others.
3. Verify exact conduit termination locations required for boxes, enclosures, and equipment installed under other sections or by others.
4. Coordinate the work with other trades to provide roof penetrations that preserve the integrity of the roofing system and do not void the roof warranty.
5. Notify Architect/Engineer of any conflicts with or deviations from Contract Documents. Obtain direction before proceeding with work.

B. Sequencing:

1. Do not begin installation of conductors and cables until installation of conduit is complete between outlet, junction and splicing points.

1.05 QUALITY ASSURANCE

A. Comply with requirements of NFPA 70.

1.06 DELIVERY, STORAGE, AND HANDLING

A. Receive, inspect, handle, and store conduit and fittings in accordance with manufacturer's instructions.

PART 2 PRODUCTS

2.01 CONDUIT APPLICATIONS

- A. Do not use conduit and associated fittings for applications other than as permitted by NFPA 70 and product listing.
- B. Unless otherwise indicated and where not otherwise restricted, use the conduit types indicated for the specified applications. Where more than one listed application applies, comply with the most restrictive requirements. Where conduit type for a particular application is not specified, use galvanized steel rigid metal conduit.
- C. Concealed Within Masonry Walls: Use galvanized steel rigid metal conduit, intermediate metal conduit (IMC), or electrical metallic tubing (EMT).
- D. Concealed Within Hollow Stud Walls: Use galvanized steel rigid metal conduit, intermediate metal conduit (IMC), or electrical metallic tubing (EMT).
- E. Concealed Above Accessible Ceilings: Use galvanized steel rigid metal conduit, intermediate metal conduit (IMC), or electrical metallic tubing (EMT).

- F. Interior, Damp or Wet Locations: Use galvanized steel rigid metal conduit.
- G. Exposed, Interior, Not Subject to Physical Damage: Use galvanized steel rigid metal conduit, intermediate metal conduit (IMC), or electrical metallic tubing (EMT).
- H. Exposed, Interior, Subject to Physical Damage: Use galvanized steel rigid metal conduit or intermediate metal conduit (IMC).
 - 1. Locations subject to physical damage include, but are not limited to:
 - a. Where exposed below 8 feet, except within electrical and communication rooms or closets.
- I. Connections to Luminaires Above Accessible Ceilings: Use flexible metal conduit.
 - 1. Maximum Length: 6 feet.
- J. Fished in Existing Walls, Where Necessary: Use flexible metal conduit.

2.02 CONDUIT REQUIREMENTS

- A. Existing Work: Where existing conduits are indicated to be reused, they may be reused only where they comply with specified requirements, are free from corrosion, and integrity is verified by pulling a mandrel through them.
- B. Provide all conduit, fittings, supports, and accessories required for a complete raceway system.
- C. Provide products listed, classified, and labeled as suitable for the purpose intended.
- D. Minimum Conduit Size, Unless Otherwise Indicated:
 - 1. Branch Circuits: 1/2 inch (16 mm) trade size.
 - 2. Branch Circuit Homeruns: 3/4 inch (21 mm) trade size.
 - 3. Control Circuits: 1/2 inch (16 mm) trade size.
 - 4. Flexible Connections to Luminaires: 3/8 inch (12 mm) trade size.
 - 5. Underground, Exterior: 1 inch (27 mm) trade size.
- E. Where conduit size is not indicated, size to comply with NFPA 70 but not less than applicable minimum size requirements specified.

2.03 GALVANIZED STEEL RIGID METAL CONDUIT (RMC)

- A. Manufacturers:
 - 1. Allied Tube & Conduit, a division of Atkore International: www.alliedeg.com/#sle.
 - 2. Nucor Tubular Products: www.nucortubular.com/#sle.
 - 3. Wheatland Tube, a division of Zekelman Industries: www.wheatland.com/#sle.
 - 4. Substitutions: See Section 01 60 00 - Product Requirements.
- B. Description: NFPA 70, Type RMC galvanized steel rigid metal conduit complying with ANSI C80.1 and listed and labeled as complying with UL 6.
- C. Fittings:
 - 1. Manufacturers:
 - a. Bridgeport Fittings Inc: www.bptfittings.com/#sle.
 - b. O-Z/Gedney, a brand of Emerson Electric Co: www.emerson.com/#sle.
 - c. Thomas & Betts Corporation: www.tnb.com/#sle.
 - d. Substitutions: See Section 01 60 00 - Product Requirements.

2. Non-Hazardous Locations: Use fittings complying with NEMA FB 1 and listed and labeled as complying with UL 514B.
3. Material: Use steel or malleable iron.
4. Connectors and Couplings: Use threaded type fittings only. Threadless set screw and compression (gland) type fittings are not permitted.

2.04 FLEXIBLE METAL CONDUIT (FMC)

A. Manufacturers:

1. AFC Cable Systems, Inc: www.afcweb.com/#sle.
2. Electri-Flex Company: www.electriflex.com/#sle.
3. International Metal Hose: www.metalhose.com/#sle.
4. Substitutions: See Section 01 60 00 - Product Requirements.

B. Description: NFPA 70, Type FMC standard wall steel flexible metal conduit listed and labeled as complying with UL 1, and listed for use in classified firestop systems to be used.

C. Fittings:

1. Manufacturers:

- a. Bridgeport Fittings Inc: www.bptfittings.com/#sle.
- b. O-Z/Gedney, a brand of Emerson Electric Co: www.emerson.com/#sle.
- c. Thomas & Betts Corporation: www.tnb.com/#sle.
- d. Substitutions: See Section 01 60 00 - Product Requirements.

2. Description: Fittings complying with NEMA FB 1 and listed and labeled as complying with UL 514B.

3. Material: Use steel or malleable iron.

2.05 ELECTRICAL METALLIC TUBING (EMT)

A. Manufacturers:

1. Allied Tube & Conduit, a division of Atkore International: www.alliedeg.com/#sle.
2. Nucor Tubular Products: www.nucortubular/#sle.
3. Wheatland Tube, a division of Zekelman Industries: www.wheatland.com/#sle.
4. Substitutions: See Section 01 60 00 - Product Requirements.

B. Description: NFPA 70, Type EMT steel electrical metallic tubing complying with ANSI C80.3 and listed and labeled as complying with UL 797.

C. Fittings:

1. Manufacturers:

- a. Bridgeport Fittings Inc: www.bptfittings.com/#sle.
- b. O-Z/Gedney, a brand of Emerson Electric Co: www.emerson.com/#sle.
- c. Thomas & Betts Corporation: www.tnb.com/#sle.
- d. Substitutions: See Section 01 60 00 - Product Requirements.

2. Description: Fittings complying with NEMA FB 1 and listed and labeled as complying with UL 514B.

3. Material: Use steel or malleable iron.

4. Connectors and Couplings: Use compression (gland) or set-screw type.

- a. Do not use indenter type connectors and couplings.

2.06 RIGID POLYVINYL CHLORIDE (PVC) CONDUIT

- A. Manufacturers:
 - 1. Cantex Inc: www.cantexinc.com/#sle.
 - 2. Carlon, a brand of Thomas & Betts Corporation: www.carlon.com/#sle.
 - 3. JM Eagle: www.jmeagle.com/#sle.
 - 4. Substitutions: See Section 01 60 00 - Product Requirements.
- B. Description: NFPA 70, Type PVC rigid polyvinyl chloride conduit complying with NEMA TC 2 and listed and labeled as complying with UL 651; Schedule 40 unless otherwise indicated, Schedule 80 where subject to physical damage; rated for use with conductors rated 90 degrees C.
- C. Fittings:
 - 1. Manufacturer: Same as manufacturer of conduit to be connected.
 - 2. Description: Fittings complying with NEMA TC 3 and listed and labeled as complying with UL 651; material to match conduit.

2.07 ACCESSORIES

- A. Corrosion Protection Tape: PVC-based, minimum thickness of 20 mil.
- B. Conduit Joint Compound: Corrosion-resistant, electrically conductive; suitable for use with the conduit to be installed.
- C. Solvent Cement for PVC Conduit and Fittings: As recommended by manufacturer of conduit and fittings to be installed.
- D. Pull Strings: Use nylon cord with average breaking strength of not less than 200 pound-force.
- E. Sealing Compound for Sealing Fittings: Listed for use with the particular fittings to be installed.
- F. Modular Seals for Conduit Penetrations: Rated for minimum of 40 psig; Suitable for the conduits to be installed.
- G. Firestop Sleeves: Listed; provide as required to preserve fire resistance rating of building elements.

PART 3 EXECUTION

3.01 EXAMINATION

- A. Verify that field measurements are as indicated.
- B. Verify that mounting surfaces are ready to receive conduits.
- C. Verify that conditions are satisfactory for installation prior to starting work.
- D. Verify that mechanical work which is likely to injure conductors has been completed.

3.02 INSTALLATION

- A. Install products in accordance with manufacturer's instructions.
- B. Perform work in accordance with NECA 1 (general workmanship).
- C. Install galvanized steel rigid metal conduit (RMC) in accordance with NECA 101.

D. Conduit Routing:

1. Unless dimensioned, conduit routing indicated is diagrammatic.
2. When conduit destination is indicated without specific routing, determine exact routing required.
3. Conceal all conduits unless specifically indicated to be exposed.
4. Conduits in the following areas may be exposed, unless otherwise indicated:
 - a. Mechanical equipment rooms.
5. Arrange conduit to maintain adequate headroom, clearances, and access.
6. Arrange conduit to provide no more than the equivalent of four 90 degree bends between pull points.
7. Arrange conduit to provide no more than 150 feet between pull points.
8. Route conduits above water and drain piping where possible.
9. Arrange conduit to prevent moisture traps. Provide drain fittings at low points and at sealing fittings where moisture may collect.
10. Maintain minimum clearance of 6 inches between conduits and piping for other systems.
11. Maintain minimum clearance of 12 inches between conduits and hot surfaces. This includes, but is not limited to:
 - a. Heaters.
 - b. Hot water piping.
 - c. Flues.
12. Group parallel conduits in the same area together on a common rack.

E. Conduit Support:

1. Secure and support conduits in accordance with NFPA 70 and Section 26 05 29 using suitable supports and methods approved by the authority having jurisdiction.
2. Provide independent support from building structure. Do not provide support from piping, ductwork, or other systems.
3. Installation Above Suspended Ceilings: Do not provide support from ceiling support system. Do not provide support from ceiling grid or allow conduits to lay on ceiling tiles.
4. Use conduit clamp to support single conduit from beam clamp or threaded rod.
5. Use trapeze hangers assembled from threaded rods and metal channel (strut) with accessory conduit clamps to support multiple parallel suspended conduits.
6. Use of spring steel conduit clips for support of conduits is not permitted.
7. Use of wire for support of conduits is not permitted.

F. Connections and Terminations:

1. Use approved zinc-rich paint or conduit joint compound on field-cut threads of galvanized steel conduits prior to making connections.
2. Where two threaded conduits must be joined and neither can be rotated, use three-piece couplings or split couplings. Do not use running threads.
3. Use suitable adapters where required to transition from one type of conduit to another.
4. Terminate threaded conduits in boxes and enclosures using threaded hubs or double lock nuts for dry locations and raintight hubs for wet locations.
5. Provide insulating bushings or insulated throats at all conduit terminations to protect conductors.
6. Secure joints and connections to provide maximum mechanical strength and electrical continuity.
7. Use suitable caps to protect installed raceway against entrance of dirt and moisture.

G. Penetrations:

1. Do not penetrate or otherwise notch or cut structural members, including footings and grade beams, without approval of Structural Engineer.
2. Make penetrations perpendicular to surfaces unless otherwise indicated.
3. Provide sleeves for penetrations as indicated or as required to facilitate installation. Set sleeves flush with exposed surfaces unless otherwise indicated or required.
4. Conceal bends for conduit risers emerging above ground.
5. Seal interior of conduits entering the building from underground at first accessible point to prevent entry of moisture and gases.
6. Where conduits penetrate waterproof membrane, seal as required to maintain integrity of membrane.

H. Condensation Prevention: Where conduits cross barriers between areas of potential substantial temperature differential, provide sealing fitting or approved sealing compound at an accessible point near the penetration to prevent condensation. This includes, but is not limited to:

1. Where conduits pass from unconditioned interior spaces into conditioned interior spaces.

I. Provide grounding and bonding in accordance with Section 26 05 26.

J. Identify conduits in accordance with Section 26 05 53.

3.03 FIELD QUALITY CONTROL

A. Repair cuts and abrasions in galvanized finishes using zinc-rich paint recommended by manufacturer. Replace components that exhibit signs of corrosion.

B. Correct deficiencies and replace damaged or defective conduits.

3.04 CLEANING

A. Clean interior of conduits to remove moisture and foreign matter.

3.05 PROTECTION

A. Immediately after installation of conduit, use suitable manufactured plugs to provide protection from entry of moisture and foreign material and do not remove until ready for installation of conductors.

END OF SECTION

SECTION 26 05 33.16
BOXES FOR ELECTRICAL SYSTEMS

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Outlet and device boxes up to 100 cubic inches, including those used as junction and pull boxes.

1.02 RELATED REQUIREMENTS

- A. Section 26 05 29 - Hangers and Supports for Electrical Systems.
- B. Section 26 05 33.13 - Conduit for Electrical Systems:
 - 1. Conduit bodies and other fittings.
 - 2. Additional requirements for locating boxes to limit conduit length and/or number of bends between pulling points.
- C. Section 26 05 53 - Identification for Electrical Systems: Identification products and requirements.
- D. Section 26 27 26 - Wiring Devices:
 - 1. Wall plates.

1.03 REFERENCE STANDARDS

- A. NECA 1 - Standard for Good Workmanship in Electrical Construction; 2015.
- B. NECA 130 - Standard for Installing and Maintaining Wiring Devices; 2016.
- C. NEMA FB 1 - Fittings, Cast Metal Boxes, and Conduit Bodies for Conduit, Electrical Metallic Tubing, and Cable; 2014.
- D. NEMA OS 1 - Sheet-Steel Outlet Boxes, Device Boxes, Covers, and Box Supports; 2013 (Reaffirmed 2020).
- E. NEMA EN 10250 - Enclosures for Electrical Equipment (1000 Volts Maximum); 2024.
- F. NFPA 70 - National Electrical Code; Most Recent Edition Adopted by Authority Having Jurisdiction, Including All Applicable Amendments and Supplements.
- G. UL 514A - Metallic Outlet Boxes; Current Edition, Including All Revisions.

1.04 ADMINISTRATIVE REQUIREMENTS

- A. Coordination:
 - 1. Coordinate the work with other trades to avoid placement of ductwork, piping, equipment, or other potential obstructions within the dedicated equipment spaces and working clearances for electrical equipment required by NFPA 70.
 - 2. Coordinate arrangement of electrical equipment with the dimensions and clearance requirements of the actual equipment to be installed.
 - 3. Coordinate minimum sizes of boxes with the actual installed arrangement of conductors, clamps, support fittings, and devices, calculated according to NFPA 70.
 - 4. Coordinate minimum sizes of pull boxes with the actual installed arrangement of connected conduits, calculated according to NFPA 70.
 - 5. Coordinate the placement of boxes with millwork, furniture, devices, equipment, etc. installed.

6. Coordinate the work with other trades to preserve insulation integrity.
7. Notify Architect/Engineer of any conflicts with or deviations from Contract Documents. Obtain direction before proceeding with work.

1.05 QUALITY ASSURANCE

- A. Comply with requirements of NFPA 70.
- B. Maintain at the project site a copy of each referenced document that prescribes execution requirements.
- C. Electrical boxes are shown on Drawings in approximate locations unless dimensioned. Install at locations required for box to serve intended purpose. Include in base bid, installation within 10 feet of location shown.

1.06 DELIVERY, STORAGE, AND HANDLING

- A. Receive, inspect, handle, and store products in accordance with manufacturer's instructions.

PART 2 PRODUCTS

2.01 BOXES

- A. General Requirements:
 1. Do not use boxes and associated accessories for applications other than as permitted by NFPA 70 and product listing.
 2. Provide all boxes, fittings, supports, and accessories required for a complete raceway system and to accommodate devices and equipment to be installed.
 3. Provide products listed, classified, and labeled as suitable for the purpose intended.
 4. Where box size is not indicated, size to comply with NFPA 70 but not less than applicable minimum size requirements specified.
 5. Provide grounding terminals within boxes where equipment grounding conductors terminate.
- B. Outlet and Device Boxes Up to 100 cubic inches, Including Those Used as Junction and Pull Boxes:
 1. Use sheet-steel boxes for dry locations unless otherwise indicated or required.
 2. Use cast aluminum boxes for damp or wet locations unless otherwise indicated or required; furnish with compatible weatherproof gasketed covers.
 3. Use shallow boxes where required by the type of wall construction.
 4. Do not use "through-wall" boxes designed for access from both sides of wall.
 5. Sheet-Steel Boxes: Comply with NEMA OS 1, and list and label as complying with UL 514A.
 6. Cast Metal Boxes: Comply with NEMA FB 1, and list and label as complying with UL 514A; furnish with threaded hubs.
 7. Boxes for Supporting Luminaires and Ceiling Fans: Listed as suitable for the type and weight of load to be supported; furnished with fixture stud to accommodate mounting of luminaire where required.
 8. Boxes for Ganged Devices: Use multigang boxes of single-piece construction. Do not use field-connected gangable boxes unless specifically indicated or permitted.
 9. Wall Plates: Comply with Section 26 27 26.
 10. Manufacturers:
 - a. Cooper Crouse-Hinds, a division of Eaton Corporation: www.cooperindustries.com/#sle.

- b. Hubbell Incorporated; RACO Products: www.hubbell-rtb.com/#sle.
- c. O-Z/Gedney, a brand of Emerson Electric Co: www.emerson.com/#sle.
- d. Thomas & Betts Corporation: www.tnb.com/#sle.
- e. Substitutions: See Section 01 60 00 - Product Requirements.

PART 3 EXECUTION

3.01 EXAMINATION

- A. Verify that field measurements are as indicated.
- B. Verify that mounting surfaces are ready to receive boxes.
- C. Verify that conditions are satisfactory for installation prior to starting work.

3.02 INSTALLATION

- A. Install products in accordance with manufacturer's instructions.
- B. Install boxes in accordance with NECA 1 (general workmanship) and, where applicable, NECA 130, including mounting heights specified in those standards where mounting heights are not indicated.
 - 1. Locate and install electrical boxes to maintain headroom and to present neat mechanical appearance.
- C. Arrange equipment to provide minimum clearances in accordance with manufacturer's instructions and NFPA 70.
- D. Flush-mount boxes in finished areas unless specifically indicated to be surface-mounted.
- E. Unless otherwise indicated, boxes may be surface-mounted where exposed conduits are indicated or permitted.
- F. Box Supports:
 - 1. Secure and support boxes in accordance with NFPA 70 and Section 26 05 29 using suitable supports and methods approved by the authority having jurisdiction.
 - 2. Provide independent support from building structure except for cast metal boxes (other than boxes used for fixture support) supported by threaded conduit connections in accordance with NFPA 70. Do not provide support from piping, ductwork, or other systems.
 - 3. Installation Above Suspended Ceilings: Do not provide support from ceiling grid or ceiling support system.
 - 4. Equipment Support Boxes: Rated for weight of equipment supported; include 2 inch male fixture studs where required.
- G. Install boxes plumb and level.
- H. Install boxes as required to preserve insulation integrity.
- I. Install permanent barrier between ganged wiring devices when voltage between adjacent devices exceeds 300 V.
- J. Install firestopping to preserve fire resistance rating of partitions and other elements.
- K. Close unused box openings.

L. Install blank wall plates on junction boxes and on outlet boxes with no devices or equipment installed or designated for future use.

M. Provide grounding and bonding in accordance with Section 26 05 26.

3.03 CLEANING

A. Clean interior of boxes to remove dirt, debris, plaster and other foreign material.

3.04 PROTECTION

A. Immediately after installation, protect boxes from entry of moisture and foreign material until ready for installation of conductors.

END OF SECTION

SECTION 26 05 53
IDENTIFICATION FOR ELECTRICAL SYSTEMS

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Electrical identification requirements.
- B. Identification nameplates and labels.
- C. Wire and cable markers.
- D. Voltage markers.

1.02 REFERENCE STANDARDS

- A. NFPA 70 - National Electrical Code; Most Recent Edition Adopted by Authority Having Jurisdiction, Including All Applicable Amendments and Supplements.

1.03 ADMINISTRATIVE REQUIREMENTS

- A. Coordination:
 - 1. Verify final designations for equipment, systems, and components to be identified prior to fabrication of identification products.
- B. Sequencing:
 - 1. Do not conceal items to be identified, in locations such as above suspended ceilings, until identification products have been installed.
 - 2. Do not install identification products until final surface finishes and painting are complete.

1.04 QUALITY ASSURANCE

- A. Comply with requirements of NFPA 70.
- B. Products: Listed and classified by Underwriters Laboratories Inc. as suitable for purpose specified on drawings.

1.05 FIELD CONDITIONS

- A. Do not install adhesive products when ambient temperature is lower than recommended by manufacturer.

PART 2 PRODUCTS

2.01 IDENTIFICATION REQUIREMENTS

- A. Identification for Conductors and Cables:
 - 1. Color Coding for Power Conductors 600 V and Less: Comply with Section 26 05 19.
 - 2. Use identification nameplate or identification label to identify color code for ungrounded and grounded power conductors inside door or enclosure at each piece of feeder or branch-circuit distribution equipment when premises has feeders or branch circuits served by more than one nominal voltage system.
 - 3. Use wire and cable markers to identify circuit number or other designation indicated for power, control, and instrumentation conductors and cables at the following locations:
 - a. At each source and load connection.

- b. Within boxes when more than one circuit is present.
 - c. Within equipment enclosures when conductors and cables enter or leave the enclosure.
- B. Identification for Raceways:
 - 1. Furnish markers for each conduit longer than 6 feet.
 - 2. Use voltage markers or color-coded bands to identify systems other than normal power system for accessible conduits at maximum intervals of 20 feet.
 - a. Color-Coded Bands: Use field-painting or vinyl color coding electrical tape to mark bands 3 inches wide.
 - 1) Color Code:
 - a) 480 Volt system: Orange.
 - b) 208 Volt system: Black.
 - c) Emergency Power System: Red.
 - d) Fire Alarm System: Red.
 - 2) Vinyl Color Coding Electrical Tape: Comply with Section 26 05 19.
- C. Identification for Boxes:
 - 1. Use voltage markers or color coded boxes to identify systems other than normal power system.
 - a. Color-Coded Boxes: Field-painted per the same color code used for raceways.

2.02 WIRE AND CABLE MARKERS

- A. Manufacturers:
 - 1. Brady Corporation: www.bradyid.com/#sle.
 - 2. HellermannTyton: www.hellermannityton.com/#sle.
 - 3. Panduit Corp: www.panduit.com/#sle.
 - 4. Substitutions: See Section 01 60 00 - Product Requirements.
- B. Markers for Conductors and Cables: Use wrap-around self-adhesive vinyl cloth type markers suitable for the conductor or cable to be identified.
- C. Markers for Conductor and Cable Bundles: Use plastic marker tags secured by nylon cable ties.
- D. Legend: Power source and circuit number or other designation indicated.
- E. Text: Use factory pre-printed or machine-printed text, all capitalized unless otherwise indicated.
- F. Minimum Text Height: 1/8 inch.
- G. Color: Black text on white background unless otherwise indicated.

2.03 VOLTAGE MARKERS

- A. Markers for Conduits: Use factory pre-printed self-adhesive vinyl, self-adhesive vinyl cloth, or vinyl snap-around type markers.
- B. Markers for Boxes and Equipment Enclosures: Use factory pre-printed self-adhesive vinyl or self-adhesive vinyl cloth type markers.
- C. Minimum Size:
 - 1. Markers for Conduits: As recommended by manufacturer for conduit size to be identified.
 - 2. Markers for Pull Boxes: 1 1/8 by 4 1/2 inches.
 - 3. Markers for Junction Boxes: 1/2 by 2 1/4 inches.

D. Legend:

1. Markers for System Identification:

E. Color: Black text on orange background unless otherwise indicated.

PART 3 EXECUTION

3.01 PREPARATION

A. Clean surfaces to receive adhesive products according to manufacturer's instructions.

3.02 INSTALLATION

A. Install products in accordance with manufacturer's instructions.

B. Install identification products to be plainly visible for examination, adjustment, servicing, and maintenance. Unless otherwise indicated, locate products as follows:

1. Surface-Mounted Equipment: Enclosure front.
2. Flush-Mounted Equipment: Inside of equipment door.
3. Branch Devices: Adjacent to device.
4. Interior Components: Legible from the point of access.
5. Conduits: Legible from the floor.
6. Boxes: Outside face of cover.
7. Conductors and Cables: Legible from the point of access.

C. Install identification products centered, level, and parallel with lines of item being identified.

D. Install self-adhesive labels and markers to achieve maximum adhesion, with no bubbles or wrinkles and edges properly sealed.

E. Install underground warning tape above buried lines with one tape per trench at 3 inches below finished grade.

3.03 FIELD QUALITY CONTROL

A. Replace self-adhesive labels and markers that exhibit bubbles, wrinkles, curling or other signs of improper adhesion.

END OF SECTION

SECTION 26 27 26 WIRING DEVICES

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Wall switches.
- B. Wall dimmers.
- C. Wall plates.

1.02 RELATED REQUIREMENTS

- A. Section 26 05 19 - Low-Voltage Electrical Power Conductors and Cables: Manufactured wiring systems for use with access floor boxes with compatible pre-wired connectors.
- B. Section 26 05 26 - Grounding and Bonding for Electrical Systems.
- C. Section 26 05 33.16 - Boxes for Electrical Systems.
- D. Section 26 05 53 - Identification for Electrical Systems: Identification products and requirements.

1.03 REFERENCE STANDARDS

- A. FS W-S-896 - Switches, Toggle (Toggle and Lock), Flush Mounted (General Specification); 2014g, with Amendment (2017).
- B. NECA 1 - Standard for Good Workmanship in Electrical Construction; 2015.
- C. NECA 130 - Standard for Installing and Maintaining Wiring Devices; 2016.
- D. NEMA WD 1 - General Color Requirements for Wiring Devices; 1999 (Reaffirmed 2020).
- E. NEMA WD 6 - Wiring Devices - Dimensional Specifications; 2021.
- F. NFPA 70 - National Electrical Code; Most Recent Edition Adopted by Authority Having Jurisdiction, Including All Applicable Amendments and Supplements.
- G. UL 20 - General-Use Snap Switches; Current Edition, Including All Revisions.
- H. UL 514D - Cover Plates for Flush-Mounted Wiring Devices; Current Edition, Including All Revisions.

1.04 ADMINISTRATIVE REQUIREMENTS

- A. Coordination:
 - 1. Coordinate the placement of outlet boxes with millwork, furniture, equipment, etc. installed under other sections or by others.
 - 2. Coordinate wiring device ratings and configurations with the electrical requirements of actual equipment to be installed.
 - 3. Coordinate the installation and preparation of uneven surfaces, such as split face block, to provide suitable surface for installation of wiring devices.
 - 4. Notify Architect/Engineer of any conflicts or deviations from Contract Documents to obtain direction prior to proceeding with work.

B. Sequencing:

1. Do not install wiring devices until final surface finishes and painting are complete.

1.05 SUBMITTALS

- A. See Section 01 30 00 - Administrative Requirements, for submittal procedures.
- B. Product Data: Provide manufacturer's catalog information showing dimensions, colors, and configurations.
- C. Manufacturer's Installation Instructions: Indicate application conditions and limitations of use stipulated by product testing agency. Include instructions for storage, handling, protection, examination, preparation, and installation of product.
- D. Operation and Maintenance Data:
 1. Wall Dimmers: Include information on operation and setting of presets.
- E. Project Record Documents: Record actual installed locations of wiring devices.

1.06 QUALITY ASSURANCE

- A. Comply with requirements of NFPA 70.
- B. Manufacturer Qualifications: Company specializing in manufacturing the products specified in this section with minimum three years documented experience.
- C. Products: Listed, classified, and labeled as suitable for the purpose intended.

1.07 DELIVERY, STORAGE, AND PROTECTION

- A. Store in a clean, dry space in original manufacturer's packaging until ready for installation.

PART 2 PRODUCTS

2.01 APPLICATIONS

- A. Provide wiring devices suitable for intended use and with ratings adequate for load served.

2.02 ALL WIRING DEVICES

- A. Provide products listed and classified by Underwriters Laboratories Inc. as suitable for the purpose specified and indicated.
- B. Finishes:
 1. All Wiring Devices: White with white aluminum wall plate unless otherwise indicated.
 2. Wiring Devices Installed in Finished Spaces: White with white aluminum wall plate unless otherwise indicated.
 3. Wiring Devices Installed in Unfinished Spaces: Gray with galvanized steel wall plate unless otherwise indicated.

2.03 WALL SWITCHES

- A. Manufacturers:
 1. Hubbell Incorporated: www.hubbell.com/#sle.
 2. Leviton Manufacturing Company, Inc: www.leviton.com/#sle.
 3. Pass & Seymour, a brand of Legrand North America, Inc: www.legrand.us/#sle.

- B. Wall Switches - General Requirements: AC only, quiet operating, general-use snap switches with silver alloy contacts, complying with NEMA WD 1 and NEMA WD 6, and listed as complying with UL 20 and where applicable, FS W-S-896; types as indicated on the drawings.
 - 1. Wiring Provisions: Terminal screws for side wiring and screw actuated binding clamp for back wiring with separate ground terminal screw.
- C. Standard Wall Switches: Industrial specification grade, 20 A, 120/277 V with standard toggle type switch actuator and maintained contacts; single pole single throw, double pole single throw, three way, or four way as indicated on the drawings.

2.04 WALL PLATES

- A. Manufacturers:
 - 1. Hubbell Incorporated: www.hubbell-wiring.com/#sle.
 - 2. Leviton Manufacturing Company, Inc: www.leviton.com/#sle.
 - 3. Pass & Seymour, a brand of Legrand North America, Inc: www.legrand.us/#sle.
- B. Wall Plates: Comply with UL 514D.
 - 1. Configuration: One piece cover as required for quantity and types of corresponding wiring devices.
 - 2. Size: Standard.
 - 3. Screws: Metal with slotted heads finished to match wall plate finish.
 - 4. Paintable metallic.
- C. Aluminum Wall Plates: Smooth satin finish, clear anodized, factory-coated to inhibit oxidation.

PART 3 EXECUTION

3.01 EXAMINATION

- A. Verify that field measurements are as indicated.
- B. Verify that outlet boxes are installed in proper locations and at proper mounting heights and are properly sized to accommodate devices and conductors in accordance with NFPA 70.
- C. Verify that wall openings are neatly cut and will be completely covered by wall plates.
- D. Verify that final surface finishes are complete, including painting.
- E. Verify that branch circuit wiring installation is completed, tested, and ready for connection to wiring devices.
- F. Verify that conditions are satisfactory for installation prior to starting work.

3.02 PREPARATION

- A. Provide extension rings to bring outlet boxes flush with finished surface.
- B. Clean dirt, debris, plaster, and other foreign materials from outlet boxes.

3.03 INSTALLATION

- A. Perform work in accordance with NECA 1 (general workmanship) and, where applicable, NECA 130, including mounting heights specified in those standards unless otherwise indicated.

- B. Coordinate locations of outlet boxes provided under Section 26 05 33.16 as required for installation of wiring devices provided under this section.
 - 1. Orient outlet boxes for vertical installation of wiring devices unless otherwise indicated.
 - 2. Where multiple receptacles, wall switches, or wall dimmers are installed at the same location and at the same mounting height, gang devices together under a common wall plate.
- C. Install wiring devices in accordance with manufacturer's instructions.
- D. Install permanent barrier between ganged wiring devices when voltage between adjacent devices exceeds 300 V.
- E. Where required, connect wiring devices using pigtails not less than 6 inches long. Do not connect more than one conductor to wiring device terminals.
- F. Connect wiring devices by wrapping conductor clockwise 3/4 turn around screw terminal and tightening to proper torque specified by the manufacturer. Where present, do not use push-in pressure terminals that do not rely on screw-actuated binding.
- G. Unless otherwise indicated, connect wiring device grounding terminal to branch circuit equipment grounding conductor and to outlet box with bonding jumper.
- H. Install wiring devices plumb and level with mounting yoke held rigidly in place.
- I. Install wall switches with OFF position down.
- J. Install wall dimmers to achieve full rating specified and indicated after derating for ganging as instructed by manufacturer.
- K. Do not share neutral conductor on branch circuits utilizing wall dimmers.
- L. Install vertically mounted receptacles with grounding pole on top and horizontally mounted receptacles with grounding pole on left.
- M. Install wall plates to fit completely flush to wall with no gaps and rough opening completely covered without strain on wall plate. Repair or reinstall improperly installed outlet boxes or improperly sized rough openings. Do not use oversized wall plates in lieu of meeting this requirement.
- N. Install blank wall plates on junction boxes and on outlet boxes with no wiring devices installed or designated for future use.

3.04 FIELD QUALITY CONTROL

- A. Inspect each wiring device for damage and defects.
- B. Operate each wall switch and wall dimmer with circuit energized to verify proper operation.
- C. Test each receptacle to verify operation and proper polarity.
- D. Correct wiring deficiencies and replace damaged or defective wiring devices.

3.05 ADJUSTING

- A. Adjust devices and wall plates to be flush and level.
- B. Adjust presets for wall dimmers according to manufacturer's instructions as directed by Architect/Engineer.

3.06 CLEANING

- A. Clean exposed surfaces to remove dirt, paint, or other foreign material and restore to match original factory finish.

END OF SECTION

**SECTION 26 51 00
INTERIOR LUMINAIRES**

PART 1 GENERAL

1.01 SECTION INCLUDES

- A. Interior luminaires.
- B. Accessories.

1.02 RELATED REQUIREMENTS

- A. Section 26 05 29 - Hangers and Supports for Electrical Systems.
- B. Section 26 05 33.16 - Boxes for Electrical Systems.
- C. Section 26 05 53 - Identification for Electrical Systems: Identification products and requirements.
- D. Section 26 27 26 - Wiring Devices: Manual wall switches and wall dimmers.

1.03 REFERENCE STANDARDS

- A. 47 CFR 15 - Radio Frequency Devices; current edition.
- B. IESNA LM-63 - ANSI Approved Standard File Format for Electronic Transfer of Photometric Data and Related Information; 2002 (Reaffirmed 2008).
- C. IES LM-79 - Approved Method: Optical and Electrical Measurements of Solid-State Lighting Products; 2019.
- D. IES LM-80 - Approved Method: Measuring Maintenance of Light Output Characteristics of Solid-State Light Sources; 2021.
- E. NECA 1 - Standard for Good Workmanship in Electrical Construction; 2015.
- F. NECA/IESNA 500 - Standard for Installing Indoor Lighting Systems; 2006.
- G. NECA/IESNA 502 - Standard for Installing Industrial Lighting Systems; 2006.
- H. NEMA LE 4 - Recessed Luminaires, Ceiling Compatibility; 2012 (Reaffirmed 2018).
- I. NFPA 70 - National Electrical Code; Most Recent Edition Adopted by Authority Having Jurisdiction, Including All Applicable Amendments and Supplements.
- J. NFPA 101 - Life Safety Code; Most Recent Edition Adopted by Authority Having Jurisdiction, Including All Applicable Amendments and Supplements.
- K. UL 924 - Emergency Lighting and Power Equipment; Current Edition, Including All Revisions.
- L. UL 1598 - Luminaires; Current Edition, Including All Revisions.
- M. UL 8750 - Light Emitting Diode (LED) Equipment for Use in Lighting Products; Current Edition, Including All Revisions.

1.04 ADMINISTRATIVE REQUIREMENTS

- A. Coordination:

1. Coordinate the installation of luminaires with mounting surfaces installed under other sections or by others. Coordinate the work with placement of supports, anchors, etc. required for mounting. Coordinate compatibility of luminaires and associated trims with mounting surfaces at installed locations.
2. Coordinate the placement of luminaires with structural members, ductwork, piping, equipment, diffusers, fire suppression system components, and other potential conflicts installed under other sections or by others.
3. Coordinate the placement of exit signs with furniture, equipment, signage or other potential obstructions to visibility installed under other sections or by others.
4. Notify Architect/Engineer of any conflicts or deviations from Contract Documents to obtain direction prior to proceeding with work.

1.05 SUBMITTALS

- A. See Section 01 30 00 - Administrative Requirements, for submittal procedures.
- B. Shop Drawings:
 1. Provide photometric calculations where luminaires are proposed for substitution upon request.
 2. Indicate construction, installation and mounting details for products.
 3. Wiring Diagrams: Submit wiring diagrams for all exit sign, night light, self-contained back-up battery lighting, battery ballasts and associated circuit breakers, programmable circuit breakers and/or emergency circuit breakers.
- C. Product Data: Provide manufacturer's standard catalog pages and data sheets including detailed information on luminaire construction, dimensions, ratings, finishes, mounting requirements, listings, service conditions, photometric performance, installed accessories, and ceiling compatibility; include model number nomenclature clearly marked with all proposed features.
 1. LED Luminaires:
 - a. Include estimated useful life, calculated based on IES LM-80 test data.
 - b. Include IES LM-79 test report upon request.
 2. Ballasts: Include wiring diagrams and list of compatible lamp configurations.
 3. Lamps: Include rated life, color temperature, color rendering index (CRI), and initial and mean lumen output.
- D. Certificates for Dimming Ballasts: Manufacturer's documentation of compatibility with dimming controls to be installed.
- E. Manufacturer's Installation Instructions: Indicate application conditions and limitations of use stipulated by product testing agency. Include instructions for storage, handling, protection, examination, preparation, and installation of product.
- F. Operation and Maintenance Data: Instructions for each product including information on replacement parts.
- G. Project Record Documents: Record actual connections and locations of luminaires and any associated remote components.

1.06 QUALITY ASSURANCE

- A. Comply with requirements of NFPA 70.

- B. Manufacturer Qualifications: Company specializing in manufacturing the products specified in this section with minimum three years documented experience.

1.07 DELIVERY, STORAGE, AND PROTECTION

- A. Receive, handle, and store products according to NECA/IESNA 500 (commercial lighting), NECA/IESNA 502 (industrial lighting), and manufacturer's written instructions.
- B. Keep products in original manufacturer's packaging and protect from damage until ready for installation.

1.08 FIELD CONDITIONS

- A. Maintain field conditions within manufacturer's required service conditions during and after installation.

1.09 WARRANTY

- A. See Section 01 78 00 - Closeout Submittals, for additional warranty requirements.
- B. Provide three year manufacturer warranty for LED luminaires, including drivers.

PART 2 PRODUCTS

2.01 LUMINAIRE TYPES

- A. Furnish products as indicated in luminaire schedule included on the drawings.
- B. Substitutions: See Section 01 60 00 - Product Requirements except where individual luminaire types are designated with substitutions not permitted.

2.02 LUMINAIRES

- A. Provide products that comply with requirements of NFPA 70.
- B. Provide products that are listed and labeled as complying with UL 1598, where applicable.
- C. Provide products listed, classified, and labeled as suitable for the purpose intended.
- D. Provide products complying with Federal Energy Management Program (FEMP) requirements.
- E. Unless otherwise indicated, provide complete luminaires including lamp(s) and all sockets, ballasts, reflectors, lenses, housings and other components required to position, energize and protect the lamp and distribute the light.
- F. Unless specifically indicated to be excluded, provide all required conduit, boxes, wiring, connectors, hardware, supports, trims, accessories, etc. as necessary for a complete operating system.
- G. Provide products suitable to withstand normal handling, installation, and service without any damage, distortion, corrosion, fading, discoloring, etc.
- H. Recessed Luminaires:
 - 1. Ceiling Compatibility: Comply with NEMA LE 4.
 - 2. Luminaires Recessed in Insulated Ceilings: Listed and labeled as IC-rated, suitable for direct contact with insulation and combustible materials.
 - 3. Luminaires Recessed in Sloped Ceilings: Provide suitable sloped ceiling adapters.

- I. LED Luminaires:
 - 1. Components: UL 8750 recognized or listed as applicable.
 - 2. Tested in accordance with IES LM-79 and IES LM-80.
 - 3. LED Estimated Useful Life: Minimum of 50,000 hours at 70 percent lumen maintenance, calculated based on IES LM-80 test data.

2.03 BALLASTS AND DRIVERS

- A. Ballasts/Drivers - General Requirements:
 - 1. Provide ballasts containing no polychlorinated biphenyls (PCBs).
 - 2. Minimum Efficiency/Efficacy: Provide ballasts complying with all current applicable federal and state ballast efficiency/efficacy standards.
- B. Dimmable LED Drivers:
 - 1. Dimming Range: Continuous dimming from 100 percent to one percent relative light output unless dimming capability to lower level is indicated, without flicker.
 - 2. Control Compatibility: Fully compatible with the dimming controls to be installed.
 - a. Wall Dimmers: See Section 26 27 26.

PART 3 EXECUTION

3.01 EXAMINATION

- A. Verify that field measurements are as indicated.
- B. Verify that outlet boxes are installed in proper locations and at proper mounting heights and are properly sized to accommodate conductors in accordance with NFPA 70.
- C. Verify that suitable support frames are installed where required.
- D. Verify that branch circuit wiring installation is completed, tested, and ready for connection to luminaires.
- E. Verify that conditions are satisfactory for installation prior to starting work.
- F. Examine substrate and supporting grids for luminaires.
- G. Examine each fixture to determine suitability for lamps specified.

3.02 PREPARATION

- A. Provide extension rings to bring outlet boxes flush with finished surface.
- B. Clean dirt, debris, plaster, and other foreign materials from outlet boxes.

3.03 INSTALLATION

- A. Coordinate locations of outlet boxes provided under Section 26 05 33.16 as required for installation of luminaires provided under this section.
- B. Perform work in accordance with NECA 1 (general workmanship).
- C. Install products in accordance with manufacturer's instructions.
- D. Install luminaires securely, in a neat and workmanlike manner, as specified in NECA 500 (commercial lighting) and NECA 502 (industrial lighting).

- E. Provide required support and attachment in accordance with Section 26 05 29.
- F. Install luminaires plumb and square and aligned with building lines and with adjacent luminaires.
- G. Locate recessed ceiling luminaires as indicated on reflected ceiling plan.
- H. Install accessories furnished with each luminaire.
- I. Make wiring connections to branch circuit using building wire with insulation suitable for temperature conditions within luminaire.
- J. Suspended Ceiling Mounted Luminaires:
 - 1. Do not use ceiling tiles to bear weight of luminaires.
 - 2. Support luminaires larger than 2 foot by 4 foot size independent of ceiling framing.
 - 3. Secure lay-in luminaires to ceiling support channels using listed safety clips at four corners.
- K. Suspended Luminaires:
 - 1. Install using the suspension method indicated, with support lengths and accessories as required for specified mounting height.
 - 2. Unless otherwise indicated, support pendants from swivel hangers.
- L. Install accessories furnished with each luminaire.
- M. Bond products and metal accessories to branch circuit equipment grounding conductor.
- N. Install lamps in each luminaire.
- O. Lamp Burn-In: Operate lamps at full output for prescribed period per manufacturer's recommendations prior to use with any dimming controls. Replace lamps that fail prematurely due to improper lamp burn-in.

3.04 FIELD QUALITY CONTROL

- A. Inspect each product for damage and defects.
- B. Operate each luminaire after installation and connection to verify proper operation.
- C. Correct wiring deficiencies and repair or replace damaged or defective products. Repair or replace excessively noisy ballasts as determined by Architect/Engineer.
- D. Energy Code Commissioning: The electrical contractor shall program, test, calibrate and confirm the proper operation and placement of all lighting controls in accordance with the International Energy Code, 2021 Edition Paragraph C408.3 "Lighting system functional testing".

3.05 ADJUSTING

- A. Aim and position adjustable luminaires to achieve desired illumination as indicated or as directed by Architect/Engineer. Secure locking fittings in place.
- B. Aim and position adjustable emergency lighting unit lamps to achieve optimum illumination of egress path as required or as directed by Architect/Engineer or authority having jurisdiction.
- C. Relamp luminaires which have failed lamps at completion of work.

3.06 CLEANING

- A. Clean surfaces according to NECA 500 (commercial lighting), NECA 502 (industrial lighting), and manufacturer's instructions to remove dirt, fingerprints, paint, or other foreign material and restore finishes to match original factory finish.

3.07 CLOSEOUT ACTIVITIES

- A. See Section 01 78 00 - Closeout Submittals, for closeout submittals.
- B. Demonstration: Demonstrate proper operation of luminaires to Architect/Engineer, and correct deficiencies or make adjustments as directed.
- C. Just prior to Substantial Completion, replace all lamps that have failed.
- D. Project record documents: Accurately record location of each luminaire.

3.08 PROTECTION

- A. Protect installed luminaires from subsequent construction operations.

END OF SECTION